

Micro Commercial Components 20736 Marilla Street Chatsworth CA 91311

Phone: (818) 701-4933 Fax: (818) 701-4939

## DTA123JCA

## **Features**

- Epitaxial Planar Die Construction
- Complementary NPN Types Available
- Built-In Biasing Resistors
- Case Material: Molded Plastic. UL Flammability Classification Rating 94V-0 and MSL Rating 1

# **Digital Transistors**

**SOT-23** 


1:IN 2:GND

### Absolute maximum ratings @ $25^{\circ}$ C

Symbol	Parameter	Min	Тур	Max	Unit	
$V_{cc}$	Supply voltage		50		V	
$V_{IN}$	Input voltage	-5		+12	V	
$P_d$	Power dissipation		200		mW	
Tj	Junction temperature		150		J	
T <sub>stg</sub>	Storage temperature	-55		150	$^{\circ}$	
Ιο	Output current		100		mA	
$I_{C(MAX)}$	Output current		100		ША	


### Electrical Characteristics @ 25 $^{\circ}$ C

Symbol	Parameter	Min	Тур	Max	Unit
$V_{l(off)}$	Input voltage (V <sub>CC</sub> =5V, I <sub>O</sub> =100 μ A)			0.5	V
$V_{I(on)}$	(V <sub>o</sub> =0.3V, I <sub>o</sub> =5mA)	1.1			V
$V_{O(on)}$	Output voltage (I <sub>O</sub> =5mA,I <sub>i</sub> =0.25mA)		0.1	0.3	V
l <sub>l</sub>	Input current (V <sub>I</sub> =5V)		-	3.6	mA
I <sub>O(off)</sub>	Output current (V <sub>CC</sub> =50V, V <sub>I</sub> =0)			0.5	μ <b>A</b>
Gı	DC current gain (V <sub>0</sub> =5V, I <sub>0</sub> =10mA)	80			
R <sub>1</sub>	Input resistance	1.54	2.2	2.86	ΚΩ
R <sub>2</sub> /R <sub>1</sub>	Resistance ratio	17	21	26	
f⊤	Transition frequency $(V_{CE}=10V, I_{E}=5mA, f=100MHz)$		250		MHz




DIMENSIONS					
	INCHES		MM		
DIM	MIN	MAX	MIN	MAX	NOTE
Α	.110	.120	2.80	3.04	
В	.083	.098	2.10	2.64	
С	.047	.055	1.20	1.40	
D	.035	.041	.89	1.03	
Е	.070	.081	1.78	2.05	
F	.018	.024	.45	.60	
G	.0005	.0039	.013	.100	
Н	.035	.044	.89	1.12	
J	.003	.007	.085	.180	
K	015	020	37	51	

#### Equivalent circuit



#### Suggested Solder Pad Layout



## DTA123JCA






Fig.1 Input voltage vs. output current (ON characteristics)




Fig.2 Output current vs. input voltage (OFF characteristics)




Fig.3 DC current gain vs. output




Fig.4 Output voltage vs. output current



## **Ordering Information**

Device	Packing
(Part Number)-TP	Tape&Reel3Kpcs/Reel

#### \*\*\*IMPORTANT NOTICE\*\*\*

Micro Commercial Components Corp. reserves the right to make changes without further notice to any product herein to make corrections, modifications, enhancements, improvements, or other changes.
Micro Commercial Components Corp. does not assume any liability arising out of the application or use of any product described herein; neither does it convey any license under its patent rights, nor the rights of others. The user of products in such applications shall assume all risks of such use and will agree to hold Micro Commercial Components Corp. and all the companies whose products are represented on our website, harmless against all damages.

#### \*\*\*APPLICATIONS DISCLAIMER\*\*\*

Products offer by *Micro Commercial Components Corp* . are not intended for use in Medical,

Aerospace or Military Applications.