


# TLV246x-Q1, TLV246xA-Q1 LOW-POWER RAIL-TO-RAIL INPUT/OUTPUT OPERATIONAL AMPLIFIERS WITH SHUTDOWN

SGLS008C – MARCH 2003 – REVISED OCTOBER 2007

- Qualified for Automotive Applications
- ESD Protection Exceeds 2000 V Per MIL-STD-883, Method 3015; Exceeds 200 V Using Machine Model ( $C = 200 \text{ pF}$ ,  $R = 0$ )
- Rail-to-Rail Output Swing
- Gain Bandwidth Product . . . 6.4 MHz
- $\pm 80\text{-mA}$  Output Drive Capability
- Supply Current . . . 500  $\mu\text{A}/\text{Channel}$
- Input Offset Voltage . . . 100  $\mu\text{V}$
- Input Noise Voltage . . . 11 nV/ $\sqrt{\text{Hz}}$
- Slew Rate . . . 1.6 V/ $\mu\text{s}$
- Micropower Shutdown Mode (TLV2460/TLV2463) . . . 0.3  $\mu\text{A}/\text{Channel}$
- Universal Operational Amplifier EVM



NC – No internal connection

## description

The devices in the TLV246x family of low-power rail-to-rail input/output operational amplifiers are specifically designed for portable applications. The input common-mode voltage range extends beyond the supply rails for maximum dynamic range in low-voltage systems. The amplifier output has rail-to-rail performance with high-output-drive capability, solving one of the limitations of older rail-to-rail input/output operational amplifiers. This rail-to-rail dynamic range and high output drive make the TLV246x ideal for buffering analog-to-digital converters.

The operational amplifier has 6.4-MHz bandwidth and 1.6-V/ $\mu\text{s}$  slew rate with only 500- $\mu\text{A}$  supply current, providing good ac performance with low power consumption. Devices are available with an optional shutdown terminal, which places the amplifier in an ultralow supply-current mode ( $I_{DD} = 0.3 \mu\text{A}/\text{channel}$ ). While in shutdown, the operational amplifier output is placed in a high-impedance state. DC applications are also well served with an input noise voltage of 11 nV/ $\sqrt{\text{Hz}}$  and input offset voltage of 100  $\mu\text{V}$ .



Please be aware that an important notice concerning availability, standard warranty, and use in critical applications of Texas Instruments semiconductor products and disclaimers thereto appears at the end of this data sheet.

UNLESS OTHERWISE NOTED this document contains PRODUCTION DATA information current as of publication date. Products conform to specifications per the terms of Texas Instruments standard warranty. Production processing does not necessarily include testing of all parameters.

Copyright © 2007 Texas Instruments Incorporated



POST OFFICE BOX 655303 • DALLAS, TEXAS 75265

**TLV246x-Q1, TLV246xA-Q1**  
**LOW-POWER RAIL-TO-RAIL INPUT/OUTPUT OPERATIONAL AMPLIFIERS**  
**WITH SHUTDOWN**

SGLS008C – MARCH 2003 – REVISED OCTOBER 2007

**ORDERING INFORMATION<sup>†</sup>**

T <sub>A</sub>	V <sub>IO</sub> MAX AT 25°C	PACKAGE <sup>‡</sup>		ORDERABLE PART NUMBER	TOP-SIDE MARKING
–40°C to 125°C	2000 µv	SOP – D	Reel of 2500	TLV2460QDRQ1	2460Q1
		TSSOP – PW	Reel of 2000	TLV2460QPWRQ1	2460Q1
		SOP – D	Reel of 2500	TLV2461QDRQ1	2461Q1
		TSSOP – PW	Reel of 2000	TLV2461QPWRQ1	2461Q1
		SOP – D	Reel of 2500	TLV2462QDRQ1	2462Q1
		TSSOP – PW	Reel of 2000	TLV2462QPWRQ1	2462Q1
		SOP – D	Reel of 2500	TLV2463QDRQ1	TLV2463Q1
		TSSOP – PW	Reel of 2000	TLV2463QPWRQ1	2463Q1
		SOP – D	Reel of 2500	TLV2464QDRQ1\$	2464Q1
		TSSOP – PW	Reel of 2000	TLV2464QPWRQ1\$	2464Q1
	1500 µv	SOP – D	Reel of 2500	TLV2460AQDRQ1	2460AQ
		TSSOP – PW	Reel of 2000	TLV2460AQPWRQ1	2460AQ
		SOP – D	Reel of 2500	TLV2461AQDRQ1	2461AQ
		TSSOP – PW	Reel of 2000	TLV2461AQPWRQ1	2461AQ
		SOP – D	Reel of 2500	TLV2462AQDRQ1	2462AQ
		TSSOP – PW	Reel of 2000	TLV2462AQPWRQ1	2462AQ
		SOP – D	Reel of 2500	TLV2463AQDRQ1	TLV2463AQ1
		TSSOP – PW	Reel of 2000	TLV2463AQPWRQ1	V2463AQ
		SOP – D	Reel of 2500	TLV2464AQDRQ1\$	V2464AQ
		TSSOP – PW	Reel of 2000	TLV2464AQPWRQ1	V2464AQ

<sup>†</sup> For the most current package and ordering information, see the Package Option Addendum at the end of this document, or see the TI web site at [www.ti.com](http://www.ti.com).

<sup>‡</sup> Package drawings, thermal data, and symbolization are available at [www.ti.com/packaging](http://www.ti.com/packaging).

\$ Product preview



POST OFFICE BOX 655303 • DALLAS, TEXAS 75265

**TLV246x-Q1, TLV246xA-Q1**  
**LOW-POWER RAIL-TO-RAIL INPUT/OUTPUT OPERATIONAL AMPLIFIERS**  
**WITH SHUTDOWN**

SGLS008C – MARCH 2003 – REVISED OCTOBER 2007

**absolute maximum ratings over operating free-air temperature range (unless otherwise noted)†**

Supply voltage‡, $V_{DD}$ .....	6 V
Differential input voltage range, $V_{ID}$ .....	-0.2 V to $V_{DD} + 0.2$ V
Input current, $I_I$ (any input) .....	$\pm 200$ mA
Output current, $I_O$ .....	$\pm 175$ mA
Total input current, $I_I$ (into $V_{DD+}$ ) .....	175 mA
Total output current, $I_O$ (out of GND) .....	175 mA
Operating free-air temperature range, $T_A$ .....	-40°C to 125°C
Maximum junction temperature, $T_J$ .....	150°C
Thermal impedance, junction to ambient§, $\theta_{JA}$ :	
D (8 pin) .....	176°C/W
D (14 pin) .....	123°C/W
PW (8 pin) .....	259°C/W
PW (14 pin) .....	174°C/W
Storage temperature range, $T_{STG}$ .....	-65°C to 150°C
Lead temperature 1.6 mm (1/16 inch) from case for 10 seconds .....	260°C

† Stresses beyond those listed under “absolute maximum ratings” may cause permanent damage to the device. These are stress ratings only, and functional operation of the device at these or any other conditions beyond those indicated under “recommended operating conditions” is not implied. Exposure to absolute-maximum-rated conditions for extended periods may affect device reliability.

‡ All voltage values, except differential voltages, are with respect to GND.

§ Package thermal impedance is calculated in accordance with JESD 51-5.

**recommended operating conditions**

		MIN	MAX	UNIT
Supply voltage, $V_{DD}$	Single supply	2.7	6	V
	Split supply	$\pm 1.35$	$\pm 3$	
Common-mode input voltage range, $V_{ICR}$		-0.2	$V_{DD} + 0.2$	V
Operating free-air temperature, $T_A$		-40	125	°C
Shutdown on/off voltage level†	$V_{IH}$	2		V
	$V_{IL}$		0.7	

† Relative to voltage on the GND terminal of the device



POST OFFICE BOX 655303 • DALLAS, TEXAS 75265

**TLV246x-Q1, TLV246xA-Q1****LOW-POWER RAIL-TO-RAIL INPUT/OUTPUT OPERATIONAL AMPLIFIERS  
WITH SHUTDOWN**

SGLS008C – MARCH 2003 – REVISED OCTOBER 2007

**electrical characteristics at specified free-air temperature,  $V_{DD} = 3\text{ V}$  (unless otherwise noted)**

PARAMETER		TEST CONDITIONS	$T_A^\dagger$	MIN	TYP	MAX	UNIT
$V_{IO}$	Input offset voltage	$V_{DD} = 3\text{ V}$ , $V_{IC} = 1.5\text{ V}$ , $V_O = 1.5\text{ V}$ , $R_S = 50\Omega$	25°C	100	2000		$\mu\text{V}$
			Full range		2200		
		TLV246xA	25°C	150	1500		
			Full range		1700		
$\alpha V_{IO}$	Temperature coefficient of input offset voltage	$V_{DD} = 3\text{ V}$ , $V_{IC} = 1.5\text{ V}$ , $V_O = 1.5\text{ V}$ , $R_S = 50\Omega$			2		$\mu\text{V}/^\circ\text{C}$
$I_{IO}$	Input offset current	$V_{DD} = 3\text{ V}$ , $V_{IC} = 1.5\text{ V}$ , $V_O = 1.5\text{ V}$ , $R_S = 50\Omega$	25°C	2.8	7		$\text{nA}$
			Full range		75		
$I_{IB}$	Input bias current	$V_{DD} = 3\text{ V}$ , $V_{IC} = 1.5\text{ V}$ , $V_O = 1.5\text{ V}$ , $R_S = 50\Omega$	25°C	4.4	14		$\text{nA}$
			Full range		75		
$V_{OH}$	High-level output voltage	$I_{OH} = -2.5\text{ mA}$	25°C	2.9			$\text{V}$
			Full range	2.8			
		$I_{OH} = -10\text{ mA}$	25°C	2.7			
			Full range	2.5			
$V_{OL}$	Low-level output voltage	$V_{IC} = 1.5\text{ V}$ , $I_{OL} = 2.5\text{ mA}$	25°C	0.1			$\text{V}$
			Full range		0.2		
		$V_{IC} = 1.5\text{ V}$ , $I_{OL} = 10\text{ mA}$	25°C	0.3			
			Full range		0.5		
$I_{OS}$	Short-circuit output current	Sourcing	25°C	50			$\text{mA}$
			Full range	20			
		Sinking	25°C	40			
			Full range	20			
$I_O$	Output current	Measured 1 V from rail	25°C		±40		$\text{mA}$
$A_{VD}$	Large-signal differential voltage amplification	$R_L = 10\text{ k}\Omega$	25°C	90	105		$\text{dB}$
			Full range	89			
$r_{i(d)}$	Differential input resistance		25°C		$10^9$		$\Omega$
$C_{i(c)}$	Common-mode input capacitance	$f = 10\text{ kHz}$	25°C		7		$\text{pF}$
$z_0$	Closed-loop output impedance	$f = 100\text{ kHz}$ , $A_V = 10$	25°C		33		$\Omega$
CMRR	Common-mode rejection ratio	$V_{ICR} = 0\text{ V}$ to $3\text{ V}$ , $R_S = 50\Omega$	25°C	66	80		$\text{dB}$
			Full range	60			
$k_{SVR}$	Supply voltage rejection ratio ( $\Delta V_{DD}/\Delta V_{IO}$ )	$V_{DD} = 2.7\text{ V}$ to $6\text{ V}$ , $V_{IC} = V_{DD}/2$ , No load	25°C	80	85		$\text{dB}$
			Full range	75			
		$V_{DD} = 3\text{ V}$ to $5\text{ V}$ , $V_{IC} = V_{DD}/2$ , No load	25°C	85	95		
			Full range	80			
$I_{DD}$	Supply current (per channels)	$V_O = 1.5\text{ V}$ , No load	25°C	0.5	0.575		$\text{mA}$
			Full range		0.9		
$I_{DD(SHDN)}$	Supply current in shutdown (TLV2460, TLV2463)	$SHDN < 0.7\text{ V}$ , Per channel in shutdown	25°C		0.3		$\mu\text{A}$
			Full range		2.5		

† Full range is  $-40^\circ\text{C}$  to  $125^\circ\text{C}$ .

POST OFFICE BOX 655303 • DALLAS, TEXAS 75265

**TLV246x-Q1, TLV246xA-Q1**  
**LOW-POWER RAIL-TO-RAIL INPUT/OUTPUT OPERATIONAL AMPLIFIERS**  
**WITH SHUTDOWN**

SGLS008C – MARCH 2003 – REVISED OCTOBER 2007

**operating characteristics at specified free-air temperature,  $V_{DD} = 3\text{ V}$  (unless otherwise noted)**

PARAMETER		TEST CONDITIONS	$T_A^\dagger$	MIN	TYP	MAX	UNIT		
SR	Slew rate at unity gain	$V_O(\text{PP}) = 2\text{ V}$ , $C_L = 160\text{ pF}$ , $R_L = 10\text{ k}\Omega$	25°C	1	1.6		V/ $\mu\text{s}$		
			Full range	0.8					
$V_n$	Equivalent input noise voltage	f = 100 Hz	25°C	16			nV/ $\sqrt{\text{Hz}}$		
		f = 1 kHz		11					
$I_n$	Equivalent input noise current	f = 1 kHz	25°C	0.13			pA/ $\sqrt{\text{Hz}}$		
THD+N	Total harmonic distortion plus noise	$V_O(\text{PP}) = 2\text{ V}$ , $R_L = 10\text{ k}\Omega$ , f = 1 kHz	25°C	0.006			%		
				0.02					
				0.08					
t(on)	Amplifier turnon time	$A_V = 1$ , $R_L = 10\text{ k}\Omega$	25°C	7.6			$\mu\text{s}$		
				7.65					
t(off)	Amplifier turnoff time	$A_V = 1$ , $R_L = 10\text{ k}\Omega$	25°C	333			ns		
				328					
				329					
Gain-bandwidth product		f = 10 kHz, $C_L = 160\text{ pF}$	$R_L = 10\text{ k}\Omega$	25°C	5.2		MHz		
t <sub>s</sub>	Settling time	$V_{(\text{STEP})\text{PP}} = 2\text{ V}$ , $A_V = -1$ , $C_L = 10\text{ pF}$ , $R_L = 10\text{ k}\Omega$	25°C	0.1%	1.47		$\mu\text{s}$		
				0.01%	1.78				
		$V_{(\text{STEP})\text{PP}} = 2\text{ V}$ , $A_V = -1$ , $C_L = 56\text{ pF}$ , $R_L = 10\text{ k}\Omega$		0.1%	1.77				
				0.01%	1.98				
$\phi_m$	Phase margin at unity gain	$R_L = 10\text{ k}\Omega$ , $C_L = 160\text{ pF}$	25°C	44			°		
Gain margin		$R_L = 10\text{ k}\Omega$ , $C_L = 160\text{ pF}$	25°C	7			dB		

† Full range is  $-40^\circ\text{C}$  to  $125^\circ\text{C}$ .

**TLV246x-Q1, TLV246xA-Q1**  
**LOW-POWER RAIL-TO-RAIL INPUT/OUTPUT OPERATIONAL AMPLIFIERS**  
**WITH SHUTDOWN**

SGLS008C – MARCH 2003 – REVISED OCTOBER 2007

**electrical characteristics at specified free-air temperature,  $V_{DD} = 5\text{ V}$  (unless otherwise noted)**

PARAMETER	TEST CONDITIONS	$T_A^\dagger$	MIN	TYP	MAX	UNIT
$V_{IO}$ Input offset voltage	$V_{DD} = 5\text{ V}$ , $V_{IC} = 2.5\text{ V}$ , $V_O = 2.5\text{ V}$ , $R_S = 50\Omega$	25°C	150	2000		$\mu\text{V}$
		Full range		2200		
	TLV246xA	25°C	150	1500		
		Full range		1700		
$\alpha V_{IO}$ Temperature coefficient of input offset voltage	$V_{DD} = 5\text{ V}$ , $V_{IC} = 2.5\text{ V}$ , $V_O = 2.5\text{ V}$ , $R_S = 50\Omega$			2		$\mu\text{V}/^\circ\text{C}$
$I_{IO}$ Input offset current	$V_{DD} = 5\text{ V}$ , $V_{IC} = 2.5\text{ V}$ , $V_O = 2.5\text{ V}$ , $R_S = 50\Omega$	25°C	0.3	7		$\text{nA}$
		Full range		60		
$I_{IB}$ Input bias current	$V_{DD} = 5\text{ V}$ , $V_{IC} = 2.5\text{ V}$ , $V_O = 2.5\text{ V}$ , $R_S = 50\Omega$	25°C	1.3	14		$\text{nA}$
		Full range		60		
$V_{OH}$ High-level output voltage	$I_{OH} = -2.5\text{ mA}$	25°C	4.9			$\text{V}$
		Full range	4.8			
	$I_{OH} = -10\text{ mA}$	25°C	4.8			
		Full range	4.7			
$V_{OL}$ Low-level output voltage	$V_{IC} = 2.5\text{ V}$ , $I_{OL} = 2.5\text{ mA}$	25°C	0.1			$\text{V}$
		Full range	0.2			
	$V_{IC} = 2.5\text{ V}$ , $I_{OL} = 10\text{ mA}$	25°C	0.2			
		Full range	0.3			
$I_{OS}$ Short-circuit output current	Sourcing	25°C	145			$\text{mA}$
		Full range	60			
	Sinking	25°C	100			
		Full range	60			
$I_O$ Output current	Measured at 1 V from rail	25°C		±80		$\text{mA}$
$A_{VD}$ Large-signal differential voltage amplification	$V_{IC} = 2.5\text{ V}$ , $R_L = 10\text{ k}\Omega$ , $V_O = 1\text{ V}$ to $4\text{ V}$	25°C	92	109		$\text{dB}$
		Full range	90			
$r_{i(d)}$ Differential input resistance		25°C		$10^9$		$\Omega$
$C_{i(c)}$ Common-mode input capacitance	$f = 10\text{ kHz}$	25°C		7		$\text{pF}$
$z_0$ Closed-loop output impedance	$f = 100\text{ kHz}$ , $A_V = 10$	25°C		29		$\Omega$
CMRR Common-mode rejection ratio	$V_{ICR} = 0\text{ V}$ to $5\text{ V}$ , $R_S = 50\Omega$	25°C	71	85		$\text{dB}$
		Full range	60			
$k_{SVR}$ Supply voltage rejection ratio ( $\Delta V_{DD}/\Delta V_{IO}$ )	$V_{DD} = 2.7\text{ V}$ to $6\text{ V}$ , $V_{IC} = V_{DD}/2$ , No load	25°C	80	85		$\text{dB}$
		Full range	75			
	$V_{DD} = 3\text{ V}$ to $5\text{ V}$ , $V_{IC} = V_{DD}/2$ , No load	25°C	85	95		$\text{dB}$
		Full range	80			
$I_{DD}$ Supply current (per channel)	$V_O = 2.5\text{ V}$ , No load	25°C		0.55	0.65	$\text{mA}$
		Full range			1	
$I_{DD(SHDN)}$ Supply current in shutdown (TLV2460, TLV2463)	$SHDN < 0.7\text{ V}$ , Per channel in shutdown	25°C		1		$\mu\text{A}$
		Full range			3	

† Full range is  $-40^\circ\text{C}$  to  $125^\circ\text{C}$ .



POST OFFICE BOX 655303 • DALLAS, TEXAS 75265

**TLV246x-Q1, TLV246xA-Q1**  
**LOW-POWER RAIL-TO-RAIL INPUT/OUTPUT OPERATIONAL AMPLIFIERS**  
**WITH SHUTDOWN**

SGLS008C – MARCH 2003 – REVISED OCTOBER 2007

**operating characteristics at specified free-air temperature,  $V_{DD} = 5\text{ V}$  (unless otherwise noted)**

PARAMETER		TEST CONDITIONS	T <sub>A</sub> <sup>†</sup>	MIN	TYP	MAX	UNIT	
SR	Slew rate at unity gain	$V_{O(PP)} = 2\text{ V}$ , $C_L = 160\text{ pF}$ , $R_L = 10\text{ k}\Omega$	25°C	1	1.6		V/ $\mu\text{s}$	
			Full range	0.8				
$V_n$	Equivalent input noise voltage	$f = 100\text{ Hz}$ $f = 1\text{ kHz}$	25°C	14			nV/ $\sqrt{\text{Hz}}$	
				11				
$I_n$	Equivalent input noise current	$f = 100\text{ Hz}$	25°C	0.13			pA/ $\sqrt{\text{Hz}}$	
THD+N	Total harmonic distortion plus noise	$V_{O(PP)} = 4\text{ V}$ , $R_L = 10\text{ k}\Omega$ , $f = 10\text{ kHz}$	25°C	0.004			%	
				0.01				
				0.04				
t(on)	Amplifier turnon time	$A_V = 1$ , $R_L = 10\text{ k}\Omega$	25°C	Both channels	7.6		$\mu\text{s}$	
				Channel 1 only, Channel 2 on	7.65			
				Channel 2 only, Channel 1 on	7.25			
t(off)	Amplifier turnoff time	$A_V = 1$ , $R_L = 10\text{ k}\Omega$	25°C	Both channels	333		ns	
				Channel 1 only, Channel 2 on	328			
				Channel 2 only, Channel 1 on	329			
Gain-bandwidth product		$f = 10\text{ kHz}$ , $C_L = 160\text{ pF}$	$R_L = 10\text{ k}\Omega$	25°C	6.4		MHz	
t <sub>s</sub>	Settling time	$V_{(STEP)PP} = 2\text{ V}$ , $A_V = -1$ , $C_L = 10\text{ pF}$ , $R_L = 10\text{ k}\Omega$	25°C	0.1%	1.53		$\mu\text{s}$	
				0.01%	1.83			
		$V_{(STEP)PP} = 2\text{ V}$ , $A_V = -1$ , $C_L = 56\text{ pF}$ , $R_L = 10\text{ k}\Omega$		0.1%	3.13			
				0.01%	3.33			
$\phi_m$	Phase margin at unity gain	$R_L = 10\text{ k}\Omega$ , $C_L = 160\text{ pF}$	25°C	45			°	
Gain margin		$R_L = 10\text{ k}\Omega$ , $C_L = 160\text{ pF}$	25°C	7			dB	

<sup>†</sup> Full range is  $-40^\circ\text{C}$  to  $125^\circ\text{C}$ .

**TLV246x-Q1, TLV246xA-Q1**  
**LOW-POWER RAIL-TO-RAIL INPUT/OUTPUT OPERATIONAL AMPLIFIERS**  
**WITH SHUTDOWN**

SGLS008C – MARCH 2003 – REVISED OCTOBER 2007

**TYPICAL CHARACTERISTICS**

**Table of Graphs**

			FIGURE
$V_{IO}$	Input offset voltage	vs Common-mode input voltage	1, 2
$I_{IB}$	Input bias current	vs Free-air temperature	3, 4
$I_{IO}$	Input offset current	vs Free-air temperature	3, 4
$V_{OH}$	High-level output voltage	vs High-level output current	5, 6
$V_{OL}$	Low-level output voltage	vs Low-level output current	7, 8
$V_{O(PP)}$	Peak-to-peak output voltage	vs Frequency	9, 10
	Open-loop gain	vs Frequency	11, 12
	Phase	vs Frequency	11, 12
$AVD$	Differential voltage amplification	vs Load resistance	13
	Capacitive load	vs Load resistance	14
$Z_0$	Output impedance	vs Frequency	15, 16
CMRR	Common-mode rejection ratio	vs Frequency	17
$k_{SVR}$	Supply-voltage rejection ratio	vs Frequency	18, 19
$I_{DD}$	Supply current	vs Supply voltage	20
		vs Free-air temperature	21
	Amplifier turnon characteristics		22
	Amplifier turnoff characteristics		23
	Supply current turnon		24
	Supply current turnoff		25
	Shutdown supply current	vs Free-air temperature	26
$SR$	Slew rate	vs Supply voltage	27
$V_n$	Equivalent input noise voltage	vs Frequency	28, 29
		vs Common-mode input voltage	30, 31
THD	Total harmonic distortion	vs Frequency	32, 33
THD+N	Total harmonic distortion plus noise	vs Peak-to-peak signal amplitude	34, 35
$\phi_m$	Phase margin	vs Frequency	11, 12
		vs Load capacitance	36
		vs Free-air temperature	37
	Gain bandwidth product	vs Supply voltage	38
		vs Free-air temperature	39
	Large signal follower		40, 41
	Small signal follower		42, 43
	Inverting large signal		44, 45
	Inverting small signal		46, 47



POST OFFICE BOX 655303 • DALLAS, TEXAS 75265

**TLV246x-Q1, TLV246xA-Q1**  
**LOW-POWER RAIL-TO-RAIL INPUT/OUTPUT OPERATIONAL AMPLIFIERS**  
**WITH SHUTDOWN**

SGLS008C – MARCH 2003 – REVISED OCTOBER 2007

**TYPICAL CHARACTERISTICS**




Figure 1




Figure 2




Figure 3




Figure 4

## TYPICAL CHARACTERISTICS




Figure 5




Figure 6




Figure 7





Figure 8


### TYPICAL CHARACTERISTICS

**PEAK-TO-PEAK OUTPUT VOLTAGE  
vs  
FREQUENCY**




**Figure 9**

**PEAK-TO-PEAK OUTPUT VOLTAGE  
vs  
FREQUENCY**



**Figure 10**

**OPEN-LOOP GAIN AND PHASE  
vs  
FREQUENCY**



**Figure 11**

**TLV246x-Q1, TLV246xA-Q1**  
**LOW-POWER RAIL-TO-RAIL INPUT/OUTPUT OPERATIONAL AMPLIFIERS**  
**WITH SHUTDOWN**

SGLS008C - MARCH 2003 - REVISED OCTOBER 2007

**TYPICAL CHARACTERISTICS**




Figure 12




Figure 13




Figure 14

**TLV246x-Q1, TLV246xA-Q1**  
**LOW-POWER RAIL-TO-RAIL INPUT/OUTPUT OPERATIONAL AMPLIFIERS**  
**WITH SHUTDOWN**

SGLS008C – MARCH 2003 – REVISED OCTOBER 2007

**TYPICAL CHARACTERISTICS**




Figure 15




Figure 16




Figure 17

**TLV246x-Q1, TLV246xA-Q1**  
**LOW-POWER RAIL-TO-RAIL INPUT/OUTPUT OPERATIONAL AMPLIFIERS**  
**WITH SHUTDOWN**

SGLS008C – MARCH 2003 – REVISED OCTOBER 2007

**TYPICAL CHARACTERISTICS**




Figure 18




Figure 19




Figure 20




Figure 21

TLV246x-Q1, TLV246xA-Q1  
**LOW-POWER RAIL-TO-RAIL INPUT/OUTPUT OPERATIONAL AMPLIFIERS  
 WITH SHUTDOWN**

SGLS008C – MARCH 2003 – REVISED OCTOBER 2007

### TYPICAL CHARACTERISTICS




Figure 22




Figure 23

### SUPPLY CURRENT WITH A SHUTDOWN PULSE TURNON CHARACTERISTICS




Figure 24

**TLV246x-Q1, TLV246xA-Q1**  
**LOW-POWER RAIL-TO-RAIL INPUT/OUTPUT OPERATIONAL AMPLIFIERS**  
**WITH SHUTDOWN**

SGLS008C – MARCH 2003 – REVISED OCTOBER 2007

**TYPICAL CHARACTERISTICS**




Figure 25




Figure 26




Figure 27

**TLV246x-Q1, TLV246xA-Q1**  
**LOW-POWER RAIL-TO-RAIL INPUT/OUTPUT OPERATIONAL AMPLIFIERS**  
**WITH SHUTDOWN**

SGLS008C – MARCH 2003 – REVISED OCTOBER 2007

**TYPICAL CHARACTERISTICS**




Figure 28




Figure 29




Figure 30




Figure 31

**TLV246x-Q1, TLV246xA-Q1**  
**LOW-POWER RAIL-TO-RAIL INPUT/OUTPUT OPERATIONAL AMPLIFIERS**  
**WITH SHUTDOWN**

SGLS008C - MARCH 2003 - REVISED OCTOBER 2007

**TYPICAL CHARACTERISTICS**




Figure 32




Figure 33




Figure 34




Figure 35

TLV246x-Q1, TLV246xA-Q1  
**LOW-POWER RAIL-TO-RAIL INPUT/OUTPUT OPERATIONAL AMPLIFIERS  
 WITH SHUTDOWN**

SGLS008C – MARCH 2003 – REVISED OCTOBER 2007

**TYPICAL CHARACTERISTICS**




Figure 36




Figure 37




Figure 38




Figure 39

**TLV246x-Q1, TLV246xA-Q1**  
**LOW-POWER RAIL-TO-RAIL INPUT/OUTPUT OPERATIONAL AMPLIFIERS**  
**WITH SHUTDOWN**

SGLS008C – MARCH 2003 – REVISED OCTOBER 2007

**TYPICAL CHARACTERISTICS**




Figure 40




Figure 41




Figure 42




Figure 43

**TLV246x-Q1, TLV246xA-Q1**  
**LOW-POWER RAIL-TO-RAIL INPUT/OUTPUT OPERATIONAL AMPLIFIERS**  
**WITH SHUTDOWN**

SGLS008C – MARCH 2003 – REVISED OCTOBER 2007

**TYPICAL CHARACTERISTICS**

**INVERTING LARGE SIGNAL**




Figure 44

**INVERTING LARGE SIGNAL**




Figure 45

**INVERTING SMALL SIGNAL**




Figure 46

**INVERTING SMALL SIGNAL**




Figure 47

## PARAMETER MEASUREMENT INFORMATION




Figure 48

## APPLICATION INFORMATION

### driving a capacitive load

When the amplifier is configured in this manner, capacitive loading directly on the output decreases the device's phase margin leading to high frequency ringing or oscillations. Therefore, for capacitive loads of greater than 10 pF, it is recommended that a resistor be placed in series ( $R_{NULL}$ ) with the output of the amplifier, as shown in Figure 49. A minimum value of  $20\ \Omega$  works well for most applications.




Figure 49. Driving a Capacitive Load

### offset voltage

The output offset voltage ( $V_{OO}$ ) is the sum of the input offset voltage ( $V_{IO}$ ) and both input bias currents ( $I_{IB}$ ) times the corresponding gains. The schematic and formula in Figure 50 can be used to calculate the output offset voltage.





Figure 50. Output Offset Voltage Model

## APPLICATION INFORMATION

### general configurations


When receiving low-level signals, limiting the bandwidth of the incoming signals into the system is often required. The simplest way to accomplish this is to place an RC filter at the noninverting terminal of the amplifier (see Figure 51).



$$\frac{V_O}{V_I} = \left(1 + \frac{R_F}{R_G}\right) \left(\frac{1}{1 + sR_1C_1}\right)$$

**Figure 51. Single-Pole Low-Pass Filter**

If even more attenuation is needed, a multiple pole filter is required. The Sallen-Key filter can be used for this task. For best results, the amplifier should have a bandwidth that is eight to ten times the filter frequency bandwidth. Failure to do this can result in phase shift of the amplifier.



**Figure 52. 2-Pole Low-Pass Sallen-Key Filter**

---

## APPLICATION INFORMATION

### shutdown function

Two members of the TLV246x family (TLV2460 and TLV2463) have a shutdown terminal for conserving battery life in portable applications. When the shutdown terminal is tied low, the supply current is reduced to  $0.3 \mu\text{A}/\text{channel}$ , the amplifier is disabled, and the outputs are placed in a high-impedance mode. To enable the amplifier, the shutdown terminal can either be left floating or pulled high. When the shutdown terminal is left floating, care should be taken to ensure that parasitic leakage current at the shutdown terminal does not inadvertently place the operational amplifier into shutdown. The shutdown terminal threshold is always referenced to  $V_{DD}/2$ . Therefore, when operating the device with split supply voltages (e.g.,  $\pm 2.5 \text{ V}$ ), the shutdown terminal must be pulled to  $V_{DD}-$  (not GND) to disable the operational amplifier.

The amplifier's output with a shutdown pulse is shown in Figures 22, 23, 24, and 25. The amplifier is powered with a single 5-V supply and configured as a noninverting configuration with a gain of 5. The amplifier turnon and turnoff times are measured from the 50% point of the shutdown pulse to the 50% point of the output waveform. The times for the single, dual, and quad are listed in the data tables.

### circuit layout considerations

To achieve the levels of high performance of the TLV246x, follow proper printed-circuit board design techniques. A general set of guidelines is given in the following.

- Ground planes – It is highly recommended that a ground plane be used on the board to provide all components with a low inductive ground connection. However, in the areas of the amplifier inputs and output, the ground plane can be removed to minimize the stray capacitance.
- Proper power supply decoupling – Use a  $6.8\text{-}\mu\text{F}$  tantalum capacitor in parallel with a  $0.1\text{-}\mu\text{F}$  ceramic capacitor on each supply terminal. It may be possible to share the tantalum among several amplifiers depending on the application, but a  $0.1\text{-}\mu\text{F}$  ceramic capacitor should always be used on the supply terminal of every amplifier. In addition, the  $0.1\text{-}\mu\text{F}$  capacitor should be placed as close as possible to the supply terminal. As this distance increases, the inductance in the connecting trace makes the capacitor less effective. The designer should strive for distances of less than 0.1 inches between the device power terminals and the ceramic capacitors.
- Sockets – Sockets can be used but are not recommended. The additional lead inductance in the socket pins often leads to stability problems. Surface-mount packages soldered directly to the printed circuit board is the best implementation.
- Short trace runs/compact part placements – Optimum high performance is achieved when stray series inductance has been minimized. To realize this, the circuit layout should be made as compact as possible, thereby minimizing the length of all trace runs. Particular attention should be paid to the inverting input of the amplifier. Its length should be kept as short as possible. This minimizes stray capacitance at the input of the amplifier.
- Surface-mount passive components – Using surface-mount passive components is recommended for high-performance amplifier circuits for several reasons. First, because of the extremely low lead inductance of surface-mount components, the problem with stray series inductance is greatly reduced. Second, the small size of surface-mount components naturally leads to a more compact layout, thereby minimizing both stray inductance and capacitance. If leaded components are used, it is recommended that the lead lengths be kept as short as possible.

## APPLICATION INFORMATION

### general power dissipation considerations

For a given  $\theta_{JA}$ , the maximum power dissipation is shown in Figure 53 and is calculated by the following formula:

$$P_D = \left( \frac{T_{MAX} - T_A}{\theta_{JA}} \right)$$

Where:

$P_D$  = Maximum power dissipation of TLV246x (watts)


$T_{MAX}$  = Absolute maximum junction temperature (150°C)

$T_A$  = Ambient free-air temperature (°C)

$\theta_{JA}$  =  $\theta_{JC} + \theta_{CA}$

$\theta_{JC}$  = Thermal coefficient from junction to case

$\theta_{CA}$  = Thermal coefficient from case to ambient air (°C/W)



NOTE A: Results are with no air flow and using JEDEC Standard Low-K test PCB.

**Figure 53. Maximum Power Dissipation vs Free-Air Temperature**

**TLV246x-Q1, TLV246xA-Q1**  
**LOW-POWER RAIL-TO-RAIL INPUT/OUTPUT OPERATIONAL AMPLIFIERS**  
**WITH SHUTDOWN**

SGLS008C – MARCH 2003 – REVISED OCTOBER 2007

---

## APPLICATION INFORMATION

### macromodel information

Macromodel information provided was derived using Microsim Parts™ Release 8, the model generation software used with Microsim PSpice™. The Boyle macromodel (see Note 2) and subcircuit in Figure 54 are generated using the TLV246x typical electrical and operating characteristics at  $T_A = 25^\circ\text{C}$ . Using this information, output simulations of the following key parameters can be generated to a tolerance of 20% (in most cases):

- Maximum positive output voltage swing
- Maximum negative output voltage swing
- Slew rate
- Quiescent power dissipation
- Input bias current
- Open-loop voltage amplification
- Unity-gain frequency
- Common-mode rejection ratio
- Phase margin
- DC output resistance
- AC output resistance
- Short-circuit output current limit

NOTE 1: G. R. Boyle, B. M. Cohn, D. O. Pederson, and J. E. Solomon, "Macromodeling of Intergrated Circuit Operational Amplifiers", *IEEE Journal of Solid-State Circuits*, SC-9, 353 (1974).


PSpice and Parts are trademarks of MicroSim Corporation.



POST OFFICE BOX 655303 • DALLAS, TEXAS 75265

**TLV246x-Q1, TLV246xA-Q1**  
**LOW-POWER RAIL-TO-RAIL INPUT/OUTPUT OPERATIONAL AMPLIFIERS**  
**WITH SHUTDOWN**

SGLS008C – MARCH 2003 – REVISED OCTOBER 2007



```
.SUBCKT TLV246X 1 2 3 4 5
  C1 11 12 2.46034E-12
  C2 6 7 10.0000E-12
  CSS 10 99 443.21E-15
  DC 5 53 DY
  DE 54 5 DY
  DLP 90 91 DX
  DLN 92 90 DX
  DP 4 3 DX
  EGND 99 0 POLY (2) (3,0) (4,0) 0 .5 .5
  FB 7 99 POLY (5) VB VC VE VLP
  + VLN 0 21.600E6 -1E3 1E3 22E6 -22E6
  GA 6 0 11 12 345.26E-6
  GCM 0 6 10 99 15.4226E-9
  ISS 10 4 DC 18.850E-6
  Hlim 90 0 VLIM 1K
  J1 11 2 10 JX1
  J2 12 1 10 JX2
  R2 6 9 100.00E3
```

```
.subckt TLV_246Y 1 2 3 4 5 6
  c1 11 12 2.4603E-12
  c2 72 7 10.000E-12
  css 10 99 443.21E-15
  dc 70 53 dy
  de 54 70 dy
  dlp 90 91 dx
  dln 92 90 dx
  dp 4 3 dx
  egnd 99 0 poly(2) (3,0) (4,0) 0 .5 .5
  fb 7 99 poly(5) vb vc ve vlp vln 0
  21.600E6 -1E3 1E3 22E6 -22E6
  ga 72 0 11 12 345.26E-6
  gcm 0 72 10 99 15.422E-9
  iss 74 4 dc 18.850E-6
  hlim 90 0 vlim 1K
  j1 11 2 10 jx1
  j2 12 1 10 jx2
  r2 72 9 100.00E3
  rd1 3 11 2.8964E3
  rd2 3 12 2.8964E3
  ro1 8 70 5.6000
  ro2 7 99 6.2000
```

	RD1	RD2	R01	R02
RP	3	10	8	7
RSS	12	99	5	99
VB	0	0	DC 0	DC 0
VC	53	53	DC .7836	DC .7836
VE	4	54	DC .7436	DC .7436
VLIM	8	7	DC 0	DC 0
VLP	0	91	DC 117	DC 117
VLN	92	0	DC 117	DC 117
.MODEL DX D (IS=800.00E-18)				
.MODEL DY D (IS=800.00E-18 Rs = 1m Cjo=10p)				
.MODEL JX1 NJF (IS=1.0000E-12 BETA=6.3239E-3				
+ VTO=-1)				
.MODEL JX2 NJF (IS=1.0000E-12 BETA=6.3239E-3				
+ VTO=-1)				
.ENDS				
rp	71	8.9127		
rss	99	10.610E6		
rs1	4	1G		
rs2	4	1G		
rs3	4	1G		
rs4	4	1G		
s1	4	6 4 s1x		
s2	5	6 4 s1x		
s3	74	6 4 s1x		
s4	4	6 4 s2x		
vb	0	dc 0		
vc	53	dc .7836		
ve	4	dc .7436		
vlim	8	dc 0		
vlp	0	dc 117		
vln	92	dc 117		
.model dx D (Is=800.00E-18)				
.model dy D (Is=800.00E-18 Rs=1m Cjo=10p)				
.model jx1 NJF (Is=1.0000E-12 Beta=6.3239E-3 Vto=-1)				
.model jx2 NJF (Is=1.0000E-12 Beta=6.3239E-3 Vto=-1)				
.model s1x VSWITCH(Roff=1E8 Ron=1.0 Voff=2.5 Von=0.0)				
.model s2x VSWITCH(Roff=1E8 Ron=1.0 Voff=0 Von=2.5)				
.ends				

Figure 54. Boyle Macromodels and Subcircuit

**PACKAGING INFORMATION**

Orderable Device	Status <sup>(1)</sup>	Package Type	Package Drawing	Pins	Package Qty	Eco Plan <sup>(2)</sup>	Lead/Ball Finish	MSL Peak Temp <sup>(3)</sup>
TLV2460AQDRG4Q1	ACTIVE	SOIC	D	8	2500	Green (RoHS & no Sb/Br)	CU NIPDAU	Level-1-260C-UNLIM
TLV2460AQDRQ1	ACTIVE	SOIC	D	8	2500	Pb-Free (RoHS)	CU NIPDAU	Level-2-250C-1 YEAR/ Level-1-235C-UNLIM
TLV2460AQPWRG4Q1	ACTIVE	TSSOP	PW	8	2000	Green (RoHS & no Sb/Br)	CU NIPDAU	Level-1-260C-UNLIM
TLV2460AQPWRQ1	ACTIVE	TSSOP	PW	8	2000	TBD	CU NIPDAU	Level-1-220C-UNLIM
TLV2460QDRG4Q1	ACTIVE	SOIC	D	8	2500	Green (RoHS & no Sb/Br)	CU NIPDAU	Level-1-260C-UNLIM
TLV2460QDRQ1	ACTIVE	SOIC	D	8	2500	Pb-Free (RoHS)	CU NIPDAU	Level-2-250C-1 YEAR/ Level-1-235C-UNLIM
TLV2460QPWRG4Q1	ACTIVE	TSSOP	PW	8	2000	Green (RoHS & no Sb/Br)	CU NIPDAU	Level-1-260C-UNLIM
TLV2460QPWRQ1	ACTIVE	TSSOP	PW	8	2000	TBD	CU NIPDAU	Level-1-220C-UNLIM
TLV2461AQDRG4Q1	ACTIVE	SOIC	D	8	2500	Green (RoHS & no Sb/Br)	CU NIPDAU	Level-1-260C-UNLIM
TLV2461AQDRQ1	ACTIVE	SOIC	D	8	2500	Pb-Free (RoHS)	CU NIPDAU	Level-2-250C-1 YEAR/ Level-1-235C-UNLIM
TLV2461AQPWRG4Q1	ACTIVE	TSSOP	PW	8	2000	Green (RoHS & no Sb/Br)	CU NIPDAU	Level-1-260C-UNLIM
TLV2461AQPWRQ1	ACTIVE	TSSOP	PW	8	2000	TBD	CU NIPDAU	Level-1-220C-UNLIM
TLV2461QDRG4Q1	ACTIVE	SOIC	D	8	2500	Green (RoHS & no Sb/Br)	CU NIPDAU	Level-1-260C-UNLIM
TLV2461QDRQ1	ACTIVE	SOIC	D	8	2500	Pb-Free (RoHS)	CU NIPDAU	Level-2-250C-1 YEAR/ Level-1-235C-UNLIM
TLV2461QPWRG4Q1	ACTIVE	TSSOP	PW	8	2000	Green (RoHS & no Sb/Br)	CU NIPDAU	Level-1-260C-UNLIM
TLV2461QPWRQ1	ACTIVE	TSSOP	PW	8	2000	TBD	CU NIPDAU	Level-1-220C-UNLIM
TLV2462AQDRG4Q1	ACTIVE	SOIC	D	8	2500	Green (RoHS & no Sb/Br)	CU NIPDAU	Level-1-260C-UNLIM
TLV2462AQDRQ1	ACTIVE	SOIC	D	8	2500	Pb-Free (RoHS)	CU NIPDAU	Level-2-250C-1 YEAR/ Level-1-235C-UNLIM
TLV2462AQPWRG4Q1	ACTIVE	TSSOP	PW	8	2000	Green (RoHS & no Sb/Br)	CU NIPDAU	Level-1-260C-UNLIM
TLV2462AQPWRQ1	ACTIVE	TSSOP	PW	8	2000	TBD	CU NIPDAU	Level-1-220C-UNLIM
TLV2462QDRG4Q1	ACTIVE	SOIC	D	8	2500	Green (RoHS & no Sb/Br)	CU NIPDAU	Level-1-260C-UNLIM
TLV2462QDRQ1	ACTIVE	SOIC	D	8	2500	Pb-Free (RoHS)	CU NIPDAU	Level-2-250C-1 YEAR/ Level-1-235C-UNLIM
TLV2462QPWRG4Q1	ACTIVE	TSSOP	PW	8	2000	Green (RoHS & no Sb/Br)	CU NIPDAU	Level-1-260C-UNLIM
TLV2462QPWRQ1	ACTIVE	TSSOP	PW	8	2000	TBD	CU NIPDAU	Level-1-220C-UNLIM
TLV2463AQDRG4Q1	ACTIVE	SOIC	D	14	2500	Green (RoHS & no Sb/Br)	CU NIPDAU	Level-1-260C-UNLIM
TLV2463AQDRQ1	ACTIVE	SOIC	D	14	2500	Pb-Free (RoHS)	CU NIPDAU	Level-2-250C-1 YEAR/ Level-1-235C-UNLIM
TLV2463AQPWRG4Q1	ACTIVE	TSSOP	PW	14	2000	Green (RoHS & no Sb/Br)	CU NIPDAU	Level-1-260C-UNLIM

Orderable Device	Status <sup>(1)</sup>	Package Type	Package Drawing	Pins	Package Qty	Eco Plan <sup>(2)</sup>	Lead/Ball Finish	MSL Peak Temp <sup>(3)</sup>
TLV2463AQPWRQ1	ACTIVE	TSSOP	PW	14	2000	TBD	CU NIPDAU	Level-1-250C-UNLIM
TLV2463QDRG4Q1	ACTIVE	SOIC	D	14	2500	Green (RoHS & no Sb/Br)	CU NIPDAU	Level-1-260C-UNLIM
TLV2463QDRQ1	ACTIVE	SOIC	D	14	2500	Pb-Free (RoHS)	CU NIPDAU	Level-2-250C-1 YEAR/Level-1-235C-UNLIM
TLV2463QPWRG4Q1	ACTIVE	TSSOP	PW	14	2000	Green (RoHS & no Sb/Br)	CU NIPDAU	Level-1-260C-UNLIM
TLV2463QPWRQ1	ACTIVE	TSSOP	PW	14	2000	TBD	Call TI	Level-1-250C-UNLIM
TLV2464AQPWRG4Q1	ACTIVE	TSSOP	PW	14	2000	Green (RoHS & no Sb/Br)	CU NIPDAU	Level-1-260C-UNLIM
TLV2464AQPWRQ1	ACTIVE	TSSOP	PW	14	2000	Pb-Free (RoHS)	CU NIPDAU	Level-1-250C-UNLIM

<sup>(1)</sup> The marketing status values are defined as follows:

**ACTIVE:** Product device recommended for new designs.

**LIFEBUY:** TI has announced that the device will be discontinued, and a lifetime-buy period is in effect.

**NRND:** Not recommended for new designs. Device is in production to support existing customers, but TI does not recommend using this part in a new design.

**PREVIEW:** Device has been announced but is not in production. Samples may or may not be available.

**OBSOLETE:** TI has discontinued the production of the device.

<sup>(2)</sup> Eco Plan - The planned eco-friendly classification: Pb-Free (RoHS), Pb-Free (RoHS Exempt), or Green (RoHS & no Sb/Br) - please check <http://www.ti.com/productcontent> for the latest availability information and additional product content details.

**TBD:** The Pb-Free/Green conversion plan has not been defined.

**Pb-Free (RoHS):** TI's terms "Lead-Free" or "Pb-Free" mean semiconductor products that are compatible with the current RoHS requirements for all 6 substances, including the requirement that lead not exceed 0.1% by weight in homogeneous materials. Where designed to be soldered at high temperatures, TI Pb-Free products are suitable for use in specified lead-free processes.

**Pb-Free (RoHS Exempt):** This component has a RoHS exemption for either 1) lead-based flip-chip solder bumps used between the die and package, or 2) lead-based die adhesive used between the die and leadframe. The component is otherwise considered Pb-Free (RoHS compatible) as defined above.

**Green (RoHS & no Sb/Br):** TI defines "Green" to mean Pb-Free (RoHS compatible), and free of Bromine (Br) and Antimony (Sb) based flame retardants (Br or Sb do not exceed 0.1% by weight in homogeneous material)

<sup>(3)</sup> MSL, Peak Temp. -- The Moisture Sensitivity Level rating according to the JEDEC industry standard classifications, and peak solder temperature.

**Important Information and Disclaimer:** The information provided on this page represents TI's knowledge and belief as of the date that it is provided. TI bases its knowledge and belief on information provided by third parties, and makes no representation or warranty as to the accuracy of such information. Efforts are underway to better integrate information from third parties. TI has taken and continues to take reasonable steps to provide representative and accurate information but may not have conducted destructive testing or chemical analysis on incoming materials and chemicals. TI and TI suppliers consider certain information to be proprietary, and thus CAS numbers and other limited information may not be available for release.

In no event shall TI's liability arising out of such information exceed the total purchase price of the TI part(s) at issue in this document sold by TI to Customer on an annual basis.

#### OTHER QUALIFIED VERSIONS OF TLV2460-Q1, TLV2460A-Q1, TLV2461-Q1, TLV2461A-Q1, TLV2462-Q1, TLV2462A-Q1, TLV2463-Q1, TLV2463A-Q1, TLV2464A-Q1 :

- Catalog: [TLV2460](#), [TLV2460A](#), [TLV2461](#), [TLV2461A](#), [TLV2462](#), [TLV2462A](#), [TLV2463](#), [TLV2463A](#), [TLV2464A](#)
- Enhanced Product: [TLV2462A-EP](#), [TLV2463A-EP](#), [TLV2464A-EP](#)
- Military: [TLV2460M](#), [TLV2460AM](#), [TLV2461M](#), [TLV2461AM](#), [TLV2462M](#), [TLV2462AM](#), [TLV2463M](#), [TLV2463AM](#)


NOTE: Qualified Version Definitions:

- Catalog - TI's standard catalog product
- Enhanced Product - Supports Defense, Aerospace and Medical Applications
- Military - QML certified for Military and Defense Applications

PW (R-PDSO-G<sup>\*\*</sup>)

## PLASTIC SMALL-OUTLINE PACKAGE


14 PINS SHOWN



- NOTES:
- All linear dimensions are in millimeters.
  - This drawing is subject to change without notice.
  - Body dimensions do not include mold flash or protrusion not to exceed 0,15.
  - Falls within JEDEC MO-153

D (R-PDSO-G8)

PLASTIC SMALL-OUTLINE PACKAGE



NOTES: A. All linear dimensions are in inches (millimeters).

B. This drawing is subject to change without notice.


C. Body length does not include mold flash, protrusions, or gate burrs. Mold flash, protrusions, or gate burrs shall not exceed .006 (0.15) per end.

D. Body width does not include interlead flash. Interlead flash shall not exceed .017 (0.43) per side.

E. Reference JEDEC MS-012 variation AA.

D (R-PDSO-G14)

PLASTIC SMALL-OUTLINE PACKAGE



NOTES: A. All linear dimensions are in inches (millimeters).

B. This drawing is subject to change without notice.

C Body length does not include mold flash, protrusions, or gate burrs. Mold flash, protrusions, or gate burrs shall not exceed .006 (0,15) per end.

D Body width does not include interlead flash. Interlead flash shall not exceed .017 (0,43) per side.  
E. Reference JEDEC MS-012 variation AB.

## **IMPORTANT NOTICE**

Texas Instruments Incorporated and its subsidiaries (TI) reserve the right to make corrections, modifications, enhancements, improvements, and other changes to its products and services at any time and to discontinue any product or service without notice. Customers should obtain the latest relevant information before placing orders and should verify that such information is current and complete. All products are sold subject to TI's terms and conditions of sale supplied at the time of order acknowledgment.

TI warrants performance of its hardware products to the specifications applicable at the time of sale in accordance with TI's standard warranty. Testing and other quality control techniques are used to the extent TI deems necessary to support this warranty. Except where mandated by government requirements, testing of all parameters of each product is not necessarily performed.

TI assumes no liability for applications assistance or customer product design. Customers are responsible for their products and applications using TI components. To minimize the risks associated with customer products and applications, customers should provide adequate design and operating safeguards.

TI does not warrant or represent that any license, either express or implied, is granted under any TI patent right, copyright, mask work right, or other TI intellectual property right relating to any combination, machine, or process in which TI products or services are used. Information published by TI regarding third-party products or services does not constitute a license from TI to use such products or services or a warranty or endorsement thereof. Use of such information may require a license from a third party under the patents or other intellectual property of the third party, or a license from TI under the patents or other intellectual property of TI.

Reproduction of TI information in TI data books or data sheets is permissible only if reproduction is without alteration and is accompanied by all associated warranties, conditions, limitations, and notices. Reproduction of this information with alteration is an unfair and deceptive business practice. TI is not responsible or liable for such altered documentation. Information of third parties may be subject to additional restrictions.

Resale of TI products or services with statements different from or beyond the parameters stated by TI for that product or service voids all express and any implied warranties for the associated TI product or service and is an unfair and deceptive business practice. TI is not responsible or liable for any such statements.

TI products are not authorized for use in safety-critical applications (such as life support) where a failure of the TI product would reasonably be expected to cause severe personal injury or death, unless officers of the parties have executed an agreement specifically governing such use. Buyers represent that they have all necessary expertise in the safety and regulatory ramifications of their applications, and acknowledge and agree that they are solely responsible for all legal, regulatory and safety-related requirements concerning their products and any use of TI products in such safety-critical applications, notwithstanding any applications-related information or support that may be provided by TI. Further, Buyers must fully indemnify TI and its representatives against any damages arising out of the use of TI products in such safety-critical applications.

TI products are neither designed nor intended for use in military/aerospace applications or environments unless the TI products are specifically designated by TI as military-grade or "enhanced plastic." Only products designated by TI as military-grade meet military specifications. Buyers acknowledge and agree that any such use of TI products which TI has not designated as military-grade is solely at the Buyer's risk, and that they are solely responsible for compliance with all legal and regulatory requirements in connection with such use.

TI products are neither designed nor intended for use in automotive applications or environments unless the specific TI products are designated by TI as compliant with ISO/TS 16949 requirements. Buyers acknowledge and agree that, if they use any non-designated products in automotive applications, TI will not be responsible for any failure to meet such requirements.

Following are URLs where you can obtain information on other Texas Instruments products and application solutions:

**Products**

Amplifiers	<a href="http://amplifier.ti.com">amplifier.ti.com</a>
Data Converters	<a href="http://dataconverter.ti.com">dataconverter.ti.com</a>
DSP	<a href="http://dsp.ti.com">dsp.ti.com</a>
Clocks and Timers	<a href="http://www.ti.com/clocks">www.ti.com/clocks</a>
Interface	<a href="http://interface.ti.com">interface.ti.com</a>
Logic	<a href="http://logic.ti.com">logic.ti.com</a>
Power Mgmt	<a href="http://power.ti.com">power.ti.com</a>
Microcontrollers	<a href="http://microcontroller.ti.com">microcontroller.ti.com</a>
RFID	<a href="http://www.ti-rfid.com">www.ti-rfid.com</a>
RF/IF and ZigBee® Solutions	<a href="http://www.ti.com/lprf">www.ti.com/lprf</a>

**Applications**

Audio	<a href="http://www.ti.com/audio">www.ti.com/audio</a>
Automotive	<a href="http://www.ti.com/automotive">www.ti.com/automotive</a>
Broadband	<a href="http://www.ti.com/broadband">www.ti.com/broadband</a>
Digital Control	<a href="http://www.ti.com/digitalcontrol">www.ti.com/digitalcontrol</a>
Medical	<a href="http://www.ti.com/medical">www.ti.com/medical</a>
Military	<a href="http://www.ti.com/military">www.ti.com/military</a>
Optical Networking	<a href="http://www.ti.com/opticalnetwork">www.ti.com/opticalnetwork</a>
Security	<a href="http://www.ti.com/security">www.ti.com/security</a>
Telephony	<a href="http://www.ti.com/telephony">www.ti.com/telephony</a>
Video & Imaging	<a href="http://www.ti.com/video">www.ti.com/video</a>
Wireless	<a href="http://www.ti.com/wireless">www.ti.com/wireless</a>

Mailing Address: Texas Instruments, Post Office Box 655303, Dallas, Texas 75265  
Copyright © 2008, Texas Instruments Incorporated