

Freescale Semiconductor, Inc. Motorola Part Numbers Affected:

Application-Specific Information

| | |
|----------------|----------------|
| MPE603RRX166LC | MPC603RRX166LC |
| MPE603RRX200LC | MPC603RRX200LC |
| MPE603RRX233LC | MPC603RRX233LC |
| MPE603RRX266LC | MPC603RRX266LC |
| MPE603RRX300LC | MPC603RRX300LC |
| | MPC603RRX200TC |
| | MPC603RRX266TC |

PowerPC 603e™ RISC Microprocessor Family: MPC603r (Goldeneye) Part Number Specification

This document defines a unique part number for a PowerPC™ PID7t-603e microprocessor manufactured by Motorola as part number MPC603R or EC603R. It describes changes to recommended operating conditions and revised electrical specifications, as applicable, from those described in the *PowerPC 603e RISC Microprocessor Family: MPC603r Hardware Specifications*.

Specifications provided in this data sheet supercede those in the *MPC603r Hardware Specifications* (order #: MPC603REC/D); specifications not addressed herein are unchanged.

Note that headings and tables in this data sheet are not numbered; however, they are intended to correspond directly to the heading or table affected in the general hardware specifications. Any additional information (including tables) not included in the hardware specification are noted.

Part numbers addressed in this document and a summary of their differences from the general specification are listed in the following table. For more detailed ordering information see "Ordering Information for the PID7t-603e Microprocessor".

. Part Numbers Addressed by this Data Sheet

| Motorola Part Number | Operating Conditions | | | Significant Differences |
|----------------------|----------------------|-----------|---------------------|---|
| | CPU Frequency | Vdd | T _J (°C) | |
| MPC603RRX166LC | 166 MHz | 2.5 ± 5%V | 0 to 105 | No electrical specification changes. |
| MPC603RRX200LC | 200 MHz | 2.5 ± 5%V | 0 to 105 | No electrical specification changes. |
| MPC603RRX233LC | 233 MHz | 2.5 ± 5%V | 0 to 105 | No electrical specification changes. |
| MPC603RRX266LC | 266 MHz | 2.5 ± 5%V | 0 to 105 | No electrical specification changes. |
| MPC603RRX300LC | 300 MHz | 2.5 ± 5%V | 0 to 105 | No electrical specification changes. |
| MPE603RRX166LC | 166 MHz | 2.5 ± 5%V | 0 to 105 | No spec changes. Floating point not guaranteed. |
| MPE603RRX200LC | 200 MHz | 2.5 ± 5%V | 0 to 105 | No spec changes. Floating point not guaranteed. |
| MPE603RRX233LC | 233 MHz | 2.5 ± 5%V | 0 to 105 | No spec changes. Floating point not guaranteed. |
| MPE603RRX266LC | 266 MHz | 2.5 ± 5%V | 0 to 105 | No spec changes. Floating point not guaranteed. |
| MPE603RRX300LC | 300 MHz | 2.5 ± 5%V | 0 to 105 | No spec changes. Floating point not guaranteed. |
| MPC603RRX200TC | 200 MHz | 2.5 ± 5%V | -40 to 105 | Extended temperature range. |
| MPC603RRX266TC | 266 MHz | 2.5 ± 5%V | -40 to 105 | Extended temperature range. |

Feature Changes

This section summarizes significant feature changes between the revision of the PID7t-603e addressed by this document and the previous revision 1.0 (XPC603RRXnnnLA or XPC603RFEnnnLA where nnn is the core frequency).

This revision was for manufacturing improvements only; there are no functional differences between this revision 2.1 and the previous revision 1.0.

This revision is functionally equivalent to the PID7v-603e (Valiant) microprocessor Revision 2.1 (XPC603PFEnnnLE/XPC603PRXnnnLE) including the following errata.

Errata

This section summarizes design defects or errors (errata) that are known to exist on this revision of the PID7t-603e. There may be additional errata that are not known or are not yet documented here which may cause the part to deviate from the functional description provided in the *MPC603e & EC603e™ RISC Microprocessor User's Manual* (order # MPC603EUM/AD Rev 1). Refer to the website at <http://www.mot.com/SPS/PowerPC/> for the latest version of this Part Number Specification or to your local Motorola sales office for later and/or more detailed description of the errata.

Freescale Semiconductor, Inc.

The known errata as of the date of this document are summarized below.

| # | Problem | Description | Impact | Solutions |
|---|--|---|--|--|
| 1 | Snoop copyback causes dcbi to broadcast wrong address. | A snoop which causes a copy-back and occurs in a one cycle window near a dcbi causes the dcbi to broadcast the address of the snoop copyback. | Only systems using both software and hardware coherency simultaneously. | Use software semaphores rather than rely on dcbi to invalidate cache lines shared across multiple processors. |
| 2 | Competition for reservation with lwarx/stwcx may cause live-lock | The problem occurs when two processors are competing on the bus for a reservation, and the bus is operating with address pipelining | System Hang | Insert a bus clock's worth of no-ops before lwarx |
| 3 | Touch load causes incorrect address to appear on memory bus | A touch load (dcbt) preceded by an instruction that generates an exception causes a random address to appear on the memory bus | Systems issuing instructions which generate mmu exceptions one cycle before using a touch load instruction | Disable touch loads with NOOPTI bit in HID0. |
| 4 | Write-thru stores followed by dcbz followed by a snoop, all to the same cache line, may cause incoherency. | The sequence of write-thru stores followed by dcbz followed by a snoop, all to the same cache line, may cause incoherency. | The write-thru store is completed after the dcbz. | Store zeroes rather than rely on dcbz to zero cache lines in areas of memory that are marked as write-thru and can be accessed via multiple logical addresses. |
| 5 | The broadcasting of dcbz instructions may retry snoop accesses indefinitely. | A sequence of broadcast bcbz instructions may retry snoop accesses indefinitely. | Snoop originator may timeout. | Disable broadcasting of dcbz by marking the memory space being addressed by the dcbz instruction as not global in the BAT or PTE. |

Electrical and Thermal Characteristics

This section provides any changes to the AC and DC electrical specifications and thermal characteristics for the PID6-603e parts described herein.

DC Electrical Characteristics

This section describes the changed thermal operating conditions for the PID7t-603e part numbers described herein.

. Recommended Operating Conditions

| Characteristic | Symbol | Value | Unit | Notes |
|-------------------------------------|----------------|------------|------|-------|
| Junction temperature | T _J | -40 to 105 | °C | |
| Note: 1. Parts with TC suffix only. | | | | |

Freescale Semiconductor, Inc.

Ordering Information


The following table provides the ordering information for the PID7t-603e part numbers described herein.

Ordering Information for the PID7t-603e Microprocessor

| Package Type | Device Rev | Process | Mask Code | CPU Frequency (MHz) | Motorola Part Number |
|--------------|------------|---------|-----------|---------------------|----------------------|
| 255 CBGA | 2.1 | PPC3.0 | 2H93J | 166 | MPC603RRX166LC |
| | | | | 200 | MPC603RRX200LC |
| | | | | 233 | MPC603RRX233LC |
| | | | | 266 | MPC603RRX266LC |
| | | | | 300 | MPC603RRX300LC |
| | | | | 166 | MPE603RRX166LC |
| | | | | 200 | MPE603RRX200LC |
| | | | | 233 | MPE603RRX233LC |
| | | | | 266 | MPE603RRX266LC |
| | | | | 300 | MPE603RRX300LC |
| | | | | 200 | MPC603RRX200TC |
| | | | | 266 | MPC603RRX266TC |

Part Marking

This section provides information on Motorola device marking standards. Parts are marked as the example shown below.



BGA

Notes:

MMMMMM is the 6-digit mask number

ATWLYYWWA is the traceability code

CCCCC is the country of assembly (this space is left blank if parts are assembled in the United States)

Part Marking for BGA Devices

Information in this document is provided solely to enable system and software implementers to use Freescale Semiconductor products. There are no express or implied copyright licenses granted hereunder to design or fabricate any integrated circuits or integrated circuits based on the information in this document. Freescale Semiconductor reserves the right to make changes without further notice to any products herein. Freescale Semiconductor makes no warranty, representation or guarantee regarding the suitability of its products for any particular purpose, nor does Freescale Semiconductor assume any liability arising out of the application or use of any product or circuit, and specifically disclaims any and all liability, including without limitation consequential or incidental damages. "Typical" parameters which may be provided in Freescale Semiconductor data sheets and/or specifications can and do vary in different applications and actual performance may vary over time. All operating parameters, including "Typicals" must be validated for each customer application by customer's technical experts. Freescale Semiconductor does not convey any license under its patent rights nor the rights of others. Freescale Semiconductor products are not designed, intended, or authorized for use as components in systems intended for surgical implant into the body, or other applications intended to support or sustain life, or for any other application in which the failure of the Freescale Semiconductor product could create a situation where personal injury or death may occur. Should Buyer purchase or use Freescale Semiconductor products for any such unintended or unauthorized application, Buyer shall indemnify and hold Freescale Semiconductor and its officers, employees, subsidiaries, affiliates, and distributors harmless against all claims, costs, damages, and expenses, and reasonable attorney fees arising out of, directly or indirectly, any claim of personal injury or death associated with such unintended or unauthorized use, even if such claim alleges that Freescale Semiconductor was negligent regarding the design or manufacture of the part.

RoHS-compliant and/or Pb-free versions of Freescale products have the functionality and electrical characteristics of their non-RoHS-compliant and/or non-Pb-free counterparts. For further information, see <http://www.freescale.com> or contact your Freescale sales representative.

For information on Freescale's Environmental Products program, go to <http://www.freescale.com/epp>.

