

**Specification Status: Released**

**Rated Operating Voltage at 20 °C (AC/DC):**  
240 V


**Maximum Interrupt Voltage / Current at 20 °C (AC/DC):**  
265 V, 1.0 A  
135 V, 20 A

**Insulating Material:**  
Cured, Flame Retardant Epoxy Polymer

**Lead Material:**  
24 AWG Sn-Plated Copper (0.52mm/0.020" nominal diameter)

**Marking:**

- Manufacturer's Mark and Voltage
- Part Identification
- Lot Identification (can be on back)



**TABLE I. DIMENSIONS:**

|      | A   |        | B   |        | C      |        | D      |     | E   |        |
|------|-----|--------|-----|--------|--------|--------|--------|-----|-----|--------|
|      | MIN | MAX    | MIN | MAX    | MIN    | MAX    | MIN    | MAX | MIN | MAX    |
| mm:  | --  | 6.9    | --  | 9.9    | 4.3    | 5.8    | 7.6    | --  | --  | 4.6    |
| in.* | --  | (0.27) | --  | (0.39) | (0.17) | (0.23) | (0.30) | --  | --  | (0.18) |

\*Rounded off approximation

**TABLE II. PERFORMANCE RATINGS @ 20 °C (as measured in Loranger P/N 02901-032-6218A):**

| HOLD CURRENT (A) | TRIP CURRENT (A) | RESISTANCE (Ω) |       | TIME TO TRIP(SEC) @ 0.25 A | POST-TRIP RESISTANCE (Ω) MAX | TRIPPED-STATE POWER DISSIPATION @ 265 V (W) |     |
|------------------|------------------|----------------|-------|----------------------------|------------------------------|---|-----|
|                  |                  | R MIN          | R MAX |                            |                              | NOM   | MAX |
| 0.05             | 0.12             | 18.5           | 31.0  | 10.0                       | 65.0                         | 0.9   | 1.1 |

\*Post Trip Resistance measured after one hour.

|                      |  |
|----------------------|--|
| Agency Recognitions: | TUV recognized. UL, CSA pending.   |
| Reference Documents: | Raychem PS300  |
| Precedence:          | This specification takes precedence over documents referenced herein               |
| Effectivity:         | Reference documents shall be the issue in effect on the date of invitation for bid |
| Warning:             | Refer to Page 2 of this document for application limitations                       |

**Materials Information**

ROHS Compliant

ELV Compliant

Pb-Free





## WARNING

### Warning: Application Limitations for the LVR Product Line

1. Users should independently evaluate the suitability of and test each product selected for their own application.
2. This product should not be used in an application where the maximum interrupt voltage or maximum interrupt current can be exceeded in a fault condition. Operation beyond the maximum ratings or improper use may result in device damage and possible electrical arcing and flame.
3. A PTC device is not a fuse - it is a nonlinear thermistor that limits current. Because under a fault condition all PTC devices go into a high resistance state but not open circuit, hazardous voltage may be present at PTC locations.
4. The devices are intended for protection against occasional overcurrent or overtemperature fault conditions and should not be used when repeated fault conditions or prolonged trip events are anticipated.
5. In most applications, power must be removed and the fault condition cleared in order to reset a PTC device. However, under certain unusual conditions, a PTC device may automatically reset (see Raychem Circuit Protection Databook). Accordingly, PTC devices should not be used in an application where an automatic reset could create a safety hazard, such as garbage disposals and blenders.
6. It is the responsibility of the user to determine the need for back up or fail safe protection to prevent damage that may occur in the event of abnormal function or failure of the PTC device.
7. Operation in circuits with a large inductance can generate a circuit voltage ( $Ldi/dt$ ) above the rated voltage of a PTC device.
8. Devices are not recommended for reflow soldering.
9. Device performance can be impacted negatively if devices are handled in a manner inconsistent with recommended electronic, thermal, or mechanical procedures for electronic components.
10. PTC devices are not recommended to be installed in applications where the device is constrained such that its PTC properties are inhibited, for example in rigid potting materials or in rigid housings which lack adequate clearance to accommodate device expansion.
11. Contamination of the PTC material with certain silicone-based oils or some aggressive solvents can adversely impact the performance of the devices.