

dsPIC30F Noise Suppression Library

Summary

The dsPIC30F Noise Suppression (NS) Library provides a function to suppress the effect of noise interfering with a speech signal. This function is useful for microphone-based applications, which have a potential for incoming speech getting corrupted by ambient noise captured by the microphone. It is especially suitable for systems in which an acoustically isolated noise reference is not available, such as:

- Hands-free Cell Phone Kits
- Speakerphones
- Intercoms
- Teleconferencing Systems
- Headsets
- As a front-end to a Speech Recognition system
- Any microphone-based application that needs to eliminate undesired noise

Description

The Noise Suppression Library is written entirely in assembly language and is highly optimized to make extensive use of the dsPIC30F DSP instruction set and advanced addressing modes. The algorithm avoids data overflow. The Noise Suppression Library provides a “NoiseSuppressionInit” function for initializing the various data structures required by the algorithm and a “NoiseSuppression” function to remove noise from a 10ms block of sampled 16-bit speech data. The user can easily call both functions through a well-documented Application Programmer's Interface (API).

The “NoiseSuppression” function is primarily a Frequency Domain algorithm. A Fast Fourier Transform (FFT) is performed on each 10ms block of data to analyze the frequency components of the signal. Thereafter, a Voice Activity Detection (VAD) algorithm is used to determine if the signal segment is speech or noise. The NS algorithm maintains a profile of the noise, and updates it every time a noise segment is detected by the VAD. Every frequency band of the input signal is then scaled according to the proportion of noise contained in that frequency band, thereby causing a significant degree of noise suppression in the resultant signal. The algorithm, thus, adapts to changes in the nature and level of noise, and does not require a separate noise reference input.

Features

Key feature of the Noise Suppression Library include:

- Only 2 user functions (“NoiseSuppressionInit” and “NoiseSuppression”), both of which can be called from either a C or assembly application program
- Full compliance with the Microchip dsPIC30F C30 Compiler, Assembler and Linker
- Simple user interface – just one library file and one header file
- Highly optimized assembly code, utilizing DSP instructions and advanced addressing modes
- Audio Bandwidth: 0-4 kHz at 8 kHz sampling rate
- 10-20 dB noise reduction, depending on type of noise
 - Several speech recordings corrupted by Babble, Car Cabin, White and Narrowband Noise included for library evaluation
- *dsPIC30F Noise Suppression Library User's Guide* is provided to help the user understand and use the library
- Demo application source code is provided with the library
- Accessory Kit available for purchase includes: an audio cable, headset, oscillators, microphone, speaker, DB9 M/F RS-232 cable, DB9M-DB9M Null Modem Adapter and can be used for library evaluation
- Contact Microchip sales for FREE evaluation samples

Resource Requirements

Computational Requirements: 3.3 MIPS

Program Flash Memory: 5 KB

RAM: 1 KB

Devices Supported


dsPIC30F6014

dsPIC30F6012

dsPIC30F5013

dsPIC30F5011

dsPIC30F4013



MICROCHIP

Development Systems

Microchip Technology Incorporated

Host System Requirements (For programming and debugging using MPLAB IDE)

- PC-compatible system with an Intel Pentium® class or higher processor, or equivalent
- A minimum of 16 MB RAM
- A minimum of 40 MB available hard drive space
- Microsoft Windows® 98, Windows 2000 or Windows XP

Part Numbers and Ordering Information:

dsPIC30F Noise Suppression Library		
Part Number	Description	Availability
SW300040-5K	dsPIC30F Noise Suppression Library Software License (Up to 5K units)	Q2/2004
SW300040-25K	dsPIC30F Noise Suppression Library Software License (5K+ to 25K units)	Q2/2004
SW300040-100K	dsPIC30F Noise Suppression Library Software License (25K+ to 100K units)	Q2/2004
AC300030	Accessory Kit (includes: audio cable, headset, oscillators, microphone, speaker, DB9 M/F RS-232 cable, DB9M-DB9M Null Modem Adapter)	Q2/2004

Note: Quantities are per project, payable as a one-time license fee based on estimated lifetime volume for products resulting from the project. Please consult the factory for quantities above 100K.

dsPIC™ Development Tools from Microchip	
MPLAB® IDE	Free
MPLAB® Visual Device Initializer (included in MPLAB® IDE)	
MPLAB® C30 C Compiler	SW006012
MPLAB® ICD 2 In-Circuit Debugger/Programmer	DV164005, DV164007
MPLAB® ICE 4000	ICE4000
MPLAB® PM3 Universal Device Programmer	DV007004
dsPIC30F Math Library (included in download of MPLAB® C30 C Compiler)	Free
dsPIC30F DSP Library	Free
dsPIC30F Peripheral Library	Free
dsPICworks™ Data Analysis and DSP Software	Free
dsPIC® Digital Filter Design	SW300001
dsPIC30F Soft-Modem Library	SW300002/3/4/5
dsPIC® Speech Recognition Library	SW300010/11/12
dsPIC® Symmetric Key Embedded Encryption Library	SW300050
dsPIC® Asymmetric Key Embedded Encryption Library	SW300055
dsPIC30F Acoustic Echo Cancellation Library	SW300060
dsPIC30F Noise Suppression Library	SW300040
CMX-RTX™ for dsPIC30F	SW300031
CMX-Tiny+™ for dsPIC30F	SW300032
CMX-Scheduler™ for dsPIC® Devices	Free at www.cmx.com
dsPICDEM™ Starter Demonstration Board	DM300016
dsPICDEM™ 28-pin Starter Demonstration Board	DM300017
dsPICDEM™ 1.1 General Purpose Development Board	DM300014
dsPICDEM™ MC1 Motor Control Development System	DM300020
dsPICDEM.net™ 1 Connectivity Development Boards	DM300004-1
dsPICDEM.net™ 2 Connectivity Development Boards	DM300004-2

Americas: Atlanta 770-640-0034 • Boston 978-692-3848 • Chicago 630-285-0071 • Dallas 972-818-7423 • Detroit 248-538-2250 • Kokomo 765-864-8360 • Los Angeles 949-263-1888 • Phoenix 480-792-7200 • San Jose 650-215-1444 • Toronto 905-673-0699 • **Asia/Pacific:** Australia 61-2-9868-6733 • India 91-80-2290061 • Japan 81-45-471- 6166 • Korea 82-2-554-7200 • Singapore 65-6334-8870 • Taiwan 886-2-2717-7175 • Taiwan-Kaohsiung 886-7-536-4818 • **China:** Beijing 86-10-85282100 • Chengdu 86-28-86766200 • Fuzhou 86-591-7503506 • Hong Kong SAR 852-2401-1200 • Qingdao 86-532-5027355 • Shanghai 86-21-6275-5700 • Shenzhen 86-755-82901380 • Shunde 86-757-28395507 • **Europe:** Austria 43-7242-2244-399 • Denmark 45-4420-9895 • France 33-1-69-53-63-20 • Germany 49-89-627-1440 • Italy 39-0331-742611 • Netherlands 31-416-690399 • United Kingdom 44-118-921-5869 (As of 3/04)

Microchip Technology Inc. • 2355 W. Chandler Blvd. • Chandler, AZ 85224-6199 USA • (480) 792-7200 • FAX (480) 792-7277

The Microchip name and logo, the Microchip logo, Accuron, dsPIC, KEELoG, microID, MPLAB, PIC, PICmicro, PICSTART, PRO MATE, PowerSmart, rPIC, and SmartShunt are registered trademarks of Microchip Technology Incorporated in the U.S.A. and other countries. AmpLab, FilterLab, MXDEV, MXLAB, PICMASTER, SEEVAL, SmartSensor and The Embedded Control Solutions Company are registered trademarks of Microchip Technology Incorporated in the U.S.A. Analog-for-the-Digital Age, Application Maestro, dsPICDEM, dsPICDEM.net, dsPICworks, ECAN, ECONOMONITOR, FanSense, FlexROM, fuzzyLAB, In-Circuit Serial Programming, ICSP, ICEPIC, Migratable Memory, MPASM, MPLIB, MPLINK, MPSIM, PICkit, PICDEM, PICDEM.net, PICLAB, PICtail, PowerCal, PowerInfo, PowerMate, PowerTool, rLAB, rPICDEM, Select Mode, Smart Serial, SmartTel and Total Endurance are trademarks of Microchip Technology Incorporated in the U.S.A. and other countries. SQTP is a service mark of Microchip Technology Incorporated in the U.S.A. All other trademarks mentioned herein are property of their respective companies.

© 2004, Microchip Technology Incorporated, Printed in the U.S.A., All Rights Reserved. 5/04

DS70124A

