

"High Frequency Ceramic Solutions"

890 MHz Filtered Directional Coupler

P/N 0898CF15A035

Detail Specification Page 1 of 3



Revised 09/17/01

Part Number	Frequency (MHz)	Insertion Loss	Return Loss	Attenuation (min.)		Coupling	Isolation
				2 x Fo	3 x Fo		
0898CF15A035_	880 - 915	0.7 dB max	14 dB min.	22 dB	17 dB	20 ± 1.0 dB	25.0 dB min.

Input Power	Impedance	Operating Temperature Range	Reel Qty
3 Watts max	50 Ω	-40 to +85°C	4000


Mechanical Dimensions

	L	W	T	a	b	c	g	p
Inches	0.079 ± .004	0.049 ± .004	0.034 ± .004	0.012 ± .004	0.008 ± .004	0.012 + .004/- .008	0.014 ± .004	0.026 ± .002
mm	2.0 ± 0.1	1.25 ± 0.1	0.85 ± 0.1	0.30 ± 0.1	0.20 ± 0.1	0.30+0.1/-0.2	0.35 ± 0.1	0.65 ± 0.05




Terminal Configuration




1	IN	4	Termination
2	GND	5	GND
3	Main Out	6	Coupled Out



Mounting Considerations

Mount these devices with brown colored side facing up. Line width should be designed to provide 50Ω impedance matching characteristics.



-  Solder Resist
-  Land
-  Through-hole (ϕ 0.3)

*Johanson Technology, Inc. reserves the right to make design changes without notice.
All sales are subject to Johanson Technology, Inc. terms and conditions.*


“High Frequency Ceramic Solutions”

890 MHz Filtered Directional Coupler


P/N 0898CF15A035

Detail Specification Page 2 of 3

P/N 0898CF15A035 Filtered Coupler Typical Coupling & Isolation



P/N 0898CF15A035 Filtered Coupler Return Loss



“High Frequency Ceramic Solutions”

890 MHz Filtered Directional Coupler

P/N 0898CF15A035

Detail Specification Page 3 of 3

P/N 0898CF15A035 Filtered Coupler
Typical Insertion Loss (Dual Scale)

