

## Family Charger

### EASY

- Drop batteries in the charger, close the lid, charging begins automatically
- Contacts auto-adjust
- LCD enables users to see charge status



### VERSATILE & FAST

#### Charges:

- 4 AA in 3hr\* (2500 mAh)
- 8 AA in 6hr (2500 mAh)
- 4 AAA in 3hr\* (900 mAh)
- 8 AAA in 6hr (900 mAh)
- 4 C/D in 6hr (2500 mAh)
- 9V 175 in 7hr (175 mAh)

\*Maximum of one battery per bay for shortest charging times



### SAFE

- Power is only on when lid is closed
- Auto shut off feature when batteries are done



#### Before Using Your Charger:

Please read all instructions and cautionary markings on the battery charger, batteries, and device.

Best used with Energizer NiMH batteries.

## North American Region

Download Instructions and Warranty Information

[English](#) | [Français](#) | [Español](#)



### Product Detail:

**Designation:** Family Charger

**Color:** Black and Silver

**Charging Current:** 2 or 4 "AA" 1100mA (1 battery per bay)  
1 or 2 "AA-C-D" 1100mA (1 battery per bay)  
6 or 8 "AA" 550mA (2 batteries per bay)  
3 or 4 "AA-C-D" 550mA (2 batteries per bay)  
1 to 4 "AAA" 450mA  
2 or 4 "AAA" 450 mA  
6 or 8 "AAA" 450 mA  
1 to 2 "9V" 30mA

AA, C, and D charging current is based on the number of batteries in each bay. One battery per bay will give maximum charging current and shortest charging times. Two batteries per bay reduces charging current therefore increasing charge time.

**Trickle Charge:** "AA-C-D" 50mA  
"AAA" 25mA  
"9V" 2mA

**Shutoff Mechanism:** Delta V Detection and Timer Control  
Delta V Detection 5mV per cell for "AA-AAA-C-D"  
Max Timer Control 2 or 4 "AA" / 1 or 2 "AA-C-D" 3 hours  
6 or 8 "AA" / 3 or 4 "AA-C-D" 6 hours  
2 or 4 or 6 or 8 "AAA" 3 hours  
1 to 2 "9V" 7 hours

**Charger Input :** DC 12V, 1A

**AC Adapter Input:** 100-240V AC 50/60Hz 0.35A

**AC Adapter Output:** DC 12V, 1A

**Weight (charger):** 460 grams (16.2 oz.)

**Dimensions (mm):** 72 x 203 x 111 (H x L x W)

**Safety Features:** Delta V Charging Cut Off  
Short Circuit and Reverse Polarity Protection  
Safety Timer to Prevent Over Charge  
Bad Battery Detection

### Important Notice

This datasheet contains information specific to products manufactured at the time of its publication.

©Energizer Holdings, Inc.

Contents herein do not constitute a warranty.