Power Schottky Rectifier

I_{FAV} = 10 A
V_{RRM} = 60 V
V_F = 0.62 V

V_{RSM} V	V_{RRM} V	Type
60	60	DSS 10-006A



TO-220 AC



A = Anode, C = Cathode , TAB = Cathode

Symbol	Conditions	Maximum Ratings	
I_{FRMS}		35	A
I_{FAV}	T_C = 160°C; rectangular, d = 0.5	10	A
I_{FSM}	T_{VJ} = 45°C; t_p = 10 ms (50 Hz), sine	120	A
E_{AS}	I_{AS} = 1 A; L = 100 µH; T_{VJ} = 25°C; non repetitive	0.05	mJ
I_{AR}	V_A = 1.5 • V_{RRM} typ.; f = 10 kHz; repetitive	0.1	A
$(dv/dt)_{cr}$		5000	V/µs
T_{VJ}		-55...+175	°C
T_{VJM}		175	°C
T_{stg}		-55...+150	°C
P_{tot}	T_C = 25°C	90	W
M_d	mounting torque	0.4...0.6	Nm
Weight	typical	2	g

Symbol	Conditions	Characteristic Values typ.	max.	
I_R ①	T_{VJ} = 25°C V_R = V_{RRM}	10	20	µA
	T_{VJ} = 125°C V_R = V_{RRM}	0.7	1.0	mA
V_F	I_F = 10 A; T_{VJ} = 125°C		0.62	V
	I_F = 10 A; T_{VJ} = 25°C		0.73	V
	I_F = 20 A; T_{VJ} = 125°C		0.70	V
R_{thJC}			1.6	K/W
R_{thCH}	with heatsink compound	0.3		K/W

Pulse test: ① Pulse Width = 5 ms, Duty Cycle < 2.0 %

Data according to IEC 60747 and per diode unless otherwise specified

Features

- International standard package
- Very low V_F
- Extremely low switching losses
- Low I_{RM}-values
- Epoxy meets UL 94V-0

Applications

- Rectifiers in switch mode power supplies (SMPS)
- Free wheeling diode in low voltage converters

Advantages

- High reliability circuit operation
- Low voltage peaks for reduced protection circuits
- Low noise switching
- Low losses

Dimensions see Outlines.pdf