

FIT80-4

Description:

The FIT80-4 toroidal inductor is specifically designed to minimize transients. It stores energy and therefore, conditions the output signal by leveling the current waveform providing a more stable current supply. Generally used in high frequency circuits, its standard design provides an economical solution in differential mode applications or as an output inductor.

Electrical Specifications (@25C):

| Min. Inductance (μH) | | Rated | Max |
|-----------------------------------|---------|---------|-------------------|
| No Bias | At Bias | DC Amps | DCR (m Ω) |
| 65.04 | 31.60 | 6.8 | 32.8 |

Note: No Bias inductance measured at .25V, 10KHZ.

Dimensions:

| A | B | C | D | E | F | G |
|------|------|------|------|------|------|-----------------|
| .975 | .625 | 1.10 | .450 | .624 | .125 | .036 \pm .003 |

Units: In inches

Weight: .045 lbs.

Technical Notes:

1. Nominal inductance values are typically 10% higher than minimal rating.
2. Biased inductance measured at rated DC amps.
3. Operation at rated current yields approximately 40°C temperature rise over 20°C ambient.

RoHS Compliance: As of manufacturing date February 2005, all standard products meet the requirements of 2002/95/EC, known as the RoHS initiative.

* Upon printing, this document is considered "uncontrolled". Please contact Triad Magnetics' website for the most current version.

