

**RABBIT**

Get Expert Advice

**1-888-411-RABT (7228)**[View Cart](#) | [Contact Us](#)

Find

[PRODUCTS](#) [SOLUTIONS](#) [SUPPORT](#) [COMPANY](#) [CHANNEL PARTNERS](#) [CAREERS](#) [ORDERING INFO](#)**▶ QUICK LINKS**

- [Low-Cost Dev Kits](#)
- [Application Kits](#)
- [RabbitCores](#)
- [Latest Downloads](#)
- [Single-Board Computers](#)
- [Rabbit Support Forums](#)
- [Training/Events](#)

## RCM3305 RabbitCore®

*Smarter. Faster. Stronger*Models [RCM3305](#), [RCM3315](#), [RCM3309](#), [RCM3319](#)[RCM3305 Description](#)[RCM3305 Specifications](#)[Buy Online >>](#)[Large View](#)

Get Rabbit eNews

**Using Rabbit?**

FREE iPod

Tell us your story  
get a **FREE** iPod

### Low-Cost Development Kits

Includes everything you need to begin development



### Description

The RCM3305 microprocessor core modules are an ideal solution for designers who want to rapidly develop serial Flash and 10/100Base-T Ethernet into their embedded application. The RCM3305 offer 4 – 8 MByte of serial Flash.

The RCM3305 come fully loaded: [Rabbit® 3000](#) @ 44.2 MHz clock, 10/100Base-T Ethernet connectivity, 512K Flash, 512K program execution SRAM, 512K data SRAM and up to 49 digital I/O shared with up to 6 serial ports operating at 1.8V (with 5V tolerant I/O). Derived from industrial client feedback and combining traditional RabbitCore product strengths into one device, the RCM3305 series takes microprocessor core modules to the next level. Software bundles can be added (see below) to this RabbitCore to enable rapid development of secure Web browser interfaces and a hierarchical file system.

### Remote Download System Sample Program (Included in Dynamic C): Reliable Firmware Updates

- Easily performs reliable firmware updates through a web browser interface
- Store and run several different downloaded programs enabling remote deployment of a multi-functional target
- Monitors downloaded application and provides email alarms for program problems

### Design Advantages

- Ideal for network-enabling security & access systems, remote automation, data logging, and industrial control when coupled with RabbitWeb™, FAT File System and SSL software modules
- Compact size simplifies integration
- Plenty of storage with safe secure firmware and data transfers
- Complete microprocessor, on-board memory, royalty-free TCP/IP stack, and hundreds of sample programs reduces time-to-market by months

RabbitCores mount directly on a user-designed motherboard and act as the controlling microprocessor for the user's system. RabbitCores can interface with all manner of CMOS-compatible digital devices through the user's motherboard. Programs are developed with our industry-proven [Dynamic C® development system](#), a C language environment that includes an editor, compiler, and in-circuit debugger (Dynamic C is included in low-cost development kits). Efficient hardware and software integration facilitates rapid design and development. User programs can be compiled, executed and debugged using Dynamic C and a programming cable—no in-circuit emulator is required. An extensive library of drivers and sample programs is provided, along with royalty-free TCP/IP stack with source.

### RabbitCore RCM3305 Specifications

Features	RCM3305	RCM3315	RCM3309	RCM3319
<b>Microprocessor</b>		Rabbit 3000 @ 44.2 MHz		
<b>Ethernet Port</b>	10/100Base-T, RJ-45, 3 LEDs	—	10/100Base-T, RJ-45, 3 LEDs	—
<b>Flash Memory</b>			512K	
<b>Data SRAM</b>			512K	
<b>Program Execution SRAM</b>			512K	
<b>Extended Memory</b>	8 MByte Serial Flash	4 MByte Serial Flash	8 MByte Serial Flash	4 MByte Serial Flash
<b>Backup Battery</b>	Connection for user-supplied battery (to support RTC and SRAM)			
<b>General-Purpose I/O</b>	49 parallel digital I/O			
<b>Additional Inputs</b>	2 Startup mode (2), reset in			
<b>Additional Outputs</b>	Status, reset out			
<b>Auxiliary I/O Bus</b>	Can be configured for 8 data lines and 6 address lines (shared with parallel I/O lines), plus I/O read/write			
<b>Serial Ports</b>	5 shared high-speed, CMOS-compatible ports:			
<b>Serial Rate</b>	Max. asynchronous baud rate = CLK/8			
<b>Slave Interface</b>	A slave port allows the core module to be used as an intelligent peripheral device slaved to a master processor, which may either be another Rabbit 3000 or any other type of processor.			
<b>Real-Time Clock</b>	Yes			
<b>Timers</b>	Ten 8-bit timers (6 cascadable), one 10-bit timer with 2 match registers			
<b>Watchdog/Supervisor</b>	Yes			
<b>Pulse-Width Modulators</b>	10-bit free-running counter and four pulse-width registers			
<b>Input Capture</b>	2-channel input capture can be used to time input signals from various port pins.			
<b>Quadrature Decoder</b>	2-channel quadrature decoder accepts inputs from external incremental encoder modules.			
<b>Power</b>	3.15-3.45 V DC 275 mA @ 3.3 V		3.15-3.45 V DC 325 mA @ 3.3 V DC	3.15-3.45 V DC 190 mA @ 3.3 V DC
<b>Operating Temp.</b>	0°C to +70°C		-40°C to +85°C	
<b>Humidity</b>	5-95%, noncondensing			
<b>Connectors- Headers</b>	Two 2 x 17 (2 mm pitch), One 2 x 5, 1.27 mm programming			

**Board Size**1.850" x 2.725" x 0.86"  
(47 mm x 69 mm x 22 mm)**Pricing (qty. 1/100)  
Part Number**\$119 / \$98  
20-101-1067\$99 / \$81  
20-101-1068\$119 / \$98  
20-101-1194\$99 / \$81  
20-101-1195**Development Kit**

101-1069