



UP008904-1007

Product Update

Errata for Z8 Encore! XP® F1680 Series Devices

Z8 Encore! XP F1680 Series MCU for All Date Codes

The errata listed in [Table 1](#) is found in the Z8 Encore! XP F1680 Series devices with any package date code. When reviewing the following errata, it is recommended that you download the most recent version of the product specification, *Z8 Encore! XP F1680 Series Product Specification* (PS0250), from www.zilog.com.

Table 1. Errata to the Z8 Encore! XP F1680 Series Devices

No.	Summary	Detailed Description
1	Voltage Brownout Protection	<p>The VBO trip point specification for the Z8F1680 is 1.6 V to 1.8 V. Zilog does not guarantee functionality of the product outside the operating range of 1.8 V to 3.6 V. Because of this, there is a risk that the product might not function properly before reaching the VBO threshold. Bits 5–7 of trim bit address 0003H are now “Reserved” to preserve the 1.6 V to 1.8 V VBO trip point specification.</p> <p>Suggested Workarounds</p> <ol style="list-style-type: none"> 1. Enable the “WDT Always On” Flash Option 0 bit 3 (VBO_AO) and the “Flash Write Protect” Flash Option 0 bit 0 (FWP) features. If the device stops functioning, then the WDT will automatically reset the device. The WDT normally requires the WDT instruction to start the WDT counting. If the device happens to reset in a non-operational region, then the WDT instruction might not get executed. Enabling the “WDT Always On” feature starts the WDT counting upon application of system power. Enabling the “Flash Write Protect” feature prevents the “WDT Always On”, the “Flash Write Protect” Flash option bits, and the Flash Program Memory from getting erased or reprogrammed accidentally when the device becomes nonfunctional. In summary, set VBO_AO=0 and FWP=0. 2. If the user application requires erasing/programming of the Flash Program Memory so that the “Flash Write Protect” feature cannot be used in the normal operating supply voltage range, then the “Flash write operation protect” Flash Option 1 bit 5 (FLASH_WR_PRO_EN) and the Low Voltage Detection (LVD) feature can be used in conjunction with the Flash Option 0 “WDT Always On” feature instead. <p>For example, the user selects the LVD threshold at 2.0 V. When the supply voltage drops below 2.0 V and into a non-operational region, this triggers the LVD to enable the “Flash Write Protect” Flash Option feature. The Flash Memory is now erase/program protected. If the device hangs up then the WDT will continue to reset the device. The supply voltage now rises above the 2.0 V. The LVD triggers the disable of the “Flash Write Protect” Flash Option feature. The WDT timeout and device resets and continues proper execution.</p> <p>Enabling these three features will protect the device, Flash Program Memory, and Flash Option bits from corruption when the device is in a non-operational supply voltage region. The LVD can be enabled in the Power Control Register by setting bit 4 (LVD/VBO) option to 0. The “Flash write operation protect” Flash Option 1 bit 5 (FLASH_WR_PRO_EN) is set to 1. In summary set LVD/VBO=0, VBO_AO=0, and FLASH_WR_PRO_EN=1.</p>
2	IRDA Infrared Encoder/Decoder not functional	<p>The IRDA Infrared Encoder/Decoder of the Z8F1680AC is currently not functional. After a power-on-reset event, the default condition of the IRDA Block is disabled. U0MDSTAT (Address = F44H) Bits 7–5 default to 000H on reset, and UOCTL1 (Address = F43H) Bit 0 defaults to 0 (disabled) on reset. Bit 0 of F43H is now “Reserved” and must be 0.</p>

Table 1. Errata to the Z8 Encore! XP F1680 Series Devices (Continued)

No.	Summary	Detailed Description
3	Flash Write Operation Protect	<p>Devices have Vth_pro too low to write protect the Flash at low voltage. Device Vth_pro is below the minimum specification limit of 2.4 V. Writing to Flash memory below 2.4 V will be unreliable and is not recommended.</p> <p>Suggested Workaround Write to the Flash memory at 2.7 V or above only.</p>
4	Analog Comparator Internal Reference	<p>The internal Vref for the Analog Comparator meets a variation of 0.88 V to 1.12 V instead of the current specification limits of 0.9 V to 1.1 V.</p> <p>Workaround None</p>



Warning: DO NOT USE IN LIFE SUPPORT

LIFE SUPPORT POLICY

ZILOG'S PRODUCTS ARE NOT AUTHORIZED FOR USE AS CRITICAL COMPONENTS IN LIFE SUPPORT DEVICES OR SYSTEMS WITHOUT THE EXPRESS PRIOR WRITTEN APPROVAL OF THE PRESIDENT AND GENERAL COUNSEL OF ZILOG CORPORATION.

As used herein

Life support devices or systems are devices which (a) are intended for surgical implant into the body, or (b) support or sustain life and whose failure to perform when properly used in accordance with instructions for use provided in the labeling can be reasonably expected to result in a significant injury to the user. A critical component is any component in a life support device or system whose failure to perform can be reasonably expected to cause the failure of the life support device or system or to affect its safety or effectiveness.

Document Disclaimer

©2007 by Zilog, Inc. All rights reserved. Information in this publication concerning the devices, applications, or technology described is intended to suggest possible uses and may be superseded. ZILOG, INC. DOES NOT ASSUME LIABILITY FOR OR PROVIDE A REPRESENTATION OF ACCURACY OF THE INFORMATION, DEVICES, OR TECHNOLOGY DESCRIBED IN THIS DOCUMENT. ZILOG ALSO DOES NOT ASSUME LIABILITY FOR INTELLECTUAL PROPERTY INFRINGEMENT RELATED IN ANY MANNER TO USE OF INFORMATION, DEVICES, OR TECHNOLOGY DESCRIBED HEREIN OR OTHERWISE. The information contained within this document has been verified according to the general principles of electrical and mechanical engineering.

Z8, Z8 Encore!, and Z8 Encore! XP are trademarks or registered trademarks of Zilog, Inc. All other product or service names are the property of their respective owners.