

Features

- Power-on reset generator with fixed delay time of 200ms Typ
- Manual reset input (APX823/APX825A)
- Reset output available in active-Low (APX823/APX824/APX825A), active-high (APX824/APX825A)
- Supply voltage supervision range 2.5V, 3V, 3.3V, 5V
- Watchdog timer
- Supply current of 30 μ A (Typ.)
- Temperature range: -40°C to 85°C
- SOT25 and SOT26: Available in "Green" Molding Compound (No Br, Sb)
- Lead Free Finish/RoHS Compliant (Note 1)

General Description

The APX823/APX824/APX825A family of supervisors provides circuit initialization and timing supervision, primarily for DSP and processor-based systems.

During power-on, RESET is asserted when supply voltage V_{CC} becomes higher than 1.1V. Thereafter, the supply voltage supervisor monitors V_{CC} and keeps RESET active as long as V_{CC} remains below the threshold voltage V_{TH} . An internal timer delays the return of the output to the inactive state (high) to ensure proper system reset. The delay time, t_d , starts after V_{CC} has risen above the threshold voltage V_{TH} . When the supply voltage drops below the threshold voltage V_{TH} , the output becomes active (low) again. No external components are required. All the devices of this family have a fixed-sense threshold voltage V_{TH} set by an internal voltage divider.

The APX823/APX825A devices incorporate a manual reset input, MR. A low level at MR causes RESET to become active. The APX824/APX825A devices include a high-level output RESET. APX823/APX824/APX825A have a watchdog timer that is periodically triggered by a positive or negative transition at WDI. When the supervising system fails to retrigger the watchdog circuit within the

time-out interval, t_{tout} , RESET becomes active for the time period t_d . This event also reinitializes the watchdog timer. Leaving WDI unconnected disables the watchdog.

In applications where the input to the WDI pin may be active (transitioning high and low) when the APX823/APX824/APX825A asserting RESET, the APX823/APX824/APX825A does not return to a non-reset state when the input voltage is above V_t .

The product spectrum is designed for supply voltage of 2.5V, 3V, 3.3V and 5V. The circuits are available in a SOT25 and SOT26 packages. The APX823/APX824/APX825A devices are characterized for operation over a temperature range of -40°C to 105°C.

Applications

- Applications Using DSPs, Microcontrollers, or Microprocessors
- Industrial Equipment
- Programmable Controls
- Automotive Systems
- Portable/Battery-Powered Equipment
- Intelligent Instruments
- Wireless Communications Systems
- Notebook/Desktop Computers


Ordering Information

APX82XX-XXXXXX				
Part No.	Voltage	Package	Lead Free	Packing
3 : APX823	46: 4.63	W5 : SOT25	G : Green	-7 : Taping
4 : APX824	44: 4.38	W6 : SOT26		
5A : APX825A	40: 4.00 31: 3.08 29: 2.93 26: 2.63 23: 2.25			

Device	Package Code	Packaging (Note 2)	7" Tape and Reel	
			Quantity	Part Number Suffix
APX823-XXW5	W5	SOT25	3000/Tape & Reel	-7
APX824-XXW5	W5	SOT25	3000/Tape & Reel	-7
APX825A-XXW6	W6	SOT26	3000/Tape & Reel	-7

Notes: 1. RoHS revision 13.2.2003. Glass and high temperature solder exemptions applied, see EU Directive Annex Notes 5 and 7.
 2. Pad layout as shown on Diodes Inc. suggested pad layout document AP02001, which can be found on our website at <http://www.diodes.com/datasheets/ap02001.pdf>.

Pin Assignments



Pin Descriptions

Name	Description
GND	Ground
RESET (RESET)	Reset output pin
V _{CC}	Operating voltage input
WDI	Watchdog input
MR	Manual reset

Absolute Maximum Ratings

(Over operating ambient temperature range, unless otherwise noted)*

Symbol	Parameter	Rating	Unit
V _{CC}	Supply Voltage	6.0	V
V _{RESET}	RESET, RESET , MR , WDI	-0.3 to (V _{CC} +0.3)	V
I _{CC}	Input Current V _{CC}	20	mA
I _O	Maximum High Output Current	20	mA
P _D	Continuous Total Power Dissipation	Derating Factor Above T _A = 25°C	SOT25 SOT26
		T _A = 25°C Power Rating	6.2 5.8
		T _A = 70°C Power Rating	SOT25 SOT26
		T _A = 85°C Power Rating	500 470 220 210
			125 120
			mW/°C
			mW
			mW
			mW
T _{OP}	Operating Junction Temperature Range	-40 to 105	°C
T _{ST}	Storage Temperature Range	-65 to 150	°C

* Stresses beyond those listed under "absolute maximum ratings" may cause permanent damage to the device. These are stress ratings only, and functional operation of the device at these or any other conditions beyond those indicated under "recommended operating conditions" is not implied. Exposure to absolute-maximum-rated conditions for extended periods may affect device reliability.

Recommended Operating Conditions

Symbol	Parameter	Min.	Max.	Unit
ESD HBM	Human Body Model ESD Protection	5		kV
ESD MM	Machine Model ESD Protection	200		V
V_{CC}	Supply Voltage	1.1	5.5	V
V_{IN}	Input Voltage	0	($V_{CC}+0.3$)	V
V_{IH}	High-level Input Voltage at MR and WDI	$0.7 \times V_{CC}$	-	V
V_{IL}	Low-level Voltage	-	$0.3 \times V_{CC}$	V
$\Delta t/\Delta V$	Input Transition Rise and Fall Rate at MR or WDI	-	100	ns/V
T_A	Operating Ambient Temperature Range	-40	85	°C
T_R	V_{CC} Rising Time ($V_{CC} = 0 \sim VT$)	-	100	V/uS

Electrical Characteristics

(Over recommended operating ambient temperature range, unless otherwise noted)

Symbol	Parameter		Test Conditions	Min	Typ.	Max	Unit
V_{OH}	High-level Output Voltage	RESET	$APX823/APX824/APX825A$ -29/26/23 $V_{CC} = V_{TH} + 0.2V$ $I_{OH} = -20\mu A$	$0.8 \times V_{CC}$	-	-	V
		RESET	$APX823/APX824/APX825A$ -40/31 $V_{CC} = V_{TH} + 0.2V$ $I_{OH} = -30\mu A$				
		RESET	$APX823/APX824/APX825A$ -46/44 $V_{CC} = V_{TH} + 0.2V$ $I_{OH} = -120\mu A$	$V_{CC} - 1.5V$	-	-	V
	Low-level Output Voltage	RESET	$APX824/APX825A$ -29/26/23 $V_{CC} \geq 1.8V$, $I_{OH} = -100\mu A$	$0.8 \times V_{CC}$	-	-	V
		RESET	$APX824/APX825A$ -46/44/40/31 $V_{CC} \geq 1.8V$, $I_{OH} = -150\mu A$				
V_{OL}	Low-level Output Voltage	RESET	$APX824/APX825A$ -29/26/23 $V_{CC} = V_{TH} + 0.2V$ $I_{OL} = 1mA$	-	-	0.4	V
		RESET	$APX824/APX825A$ -40/31 $V_{CC} = V_{TH} + 0.2V$ $I_{OL} = 1.2mA$				
		RESET	$APX824/APX825A$ -46/44 $V_{CC} = V_{TH} + 0.2V$ $I_{OL} = 3mA$				
	RESET	RESET	$APX823/APX824/APX825A$ -29/26/23 $V_{CC} = V_{TH} - 0.2V$ $I_{OL} = 1mA$	-	-	0.4	V
		RESET	$APX823/APX824/APX825A$ -40/31 $V_{CC} = V_{TH} - 0.2V$ $I_{OL} = 1.2mA$				
	RESET	RESET	$APX823/APX824/APX825A$ -46/44 $V_{CC} = V_{TH} - 0.2V$ $I_{OL} = 3mA$	-	-	-	V
V_{RESET}	Power-up Reset Voltage (see Note 3)		$V_{CC} \geq 1.1V$, $I_{OL} = 20\mu A$	-	-	0.4	V

Notes: 3. The lowest supply voltage at which RESET becomes active. T_R , $V_{CC} \geq 15\mu s/V$.

Electrical Characteristics (Continued)

(Over recommended operating ambient temperature range, unless otherwise noted)

Symbol	Parameter	Test Conditions	Min	Typ.	Max	Unit	
V_{TH}	Negative-going Input Threshold Voltage (see Note 4)	$T_A = 0^\circ\text{C} - 85^\circ\text{C}$	2.21	2.25	2.30	V	
			2.59	2.63	2.69		
			2.88	2.93	3.00		
			3.02	3.08	3.15		
			3.93	4.00	4.08		
			4.31	4.38	4.47		
			4.56	4.63	4.72		
		$T_A = -40^\circ\text{C} - 85^\circ\text{C}$	2.20	2.25	2.30	V	
			2.57	2.63	2.69		
			2.86	2.93	3.00		
			3.00	3.08	3.15		
			3.92	4.00	4.08		
			4.29	4.38	4.47		
			4.54	4.63	4.72		
V_{hys}	Hysteresis at V_{CC} Input	APX823/APX824/APX825A -23 APX823/APX824/APX825A -26 APX823/APX824/APX825A -29 APX823/APX824/APX825A -31	-	50	-	mV	
			-	50	-		
			-	50	-		
			-	50	-		
		APX823/APX824/APX825A -40 APX823/APX824/APX825A -44 APX823/APX824/APX825A -46	-	50	-		
			-	50	-		
			-	50	-		
T_S	Set-up Time	$V_{CC} = V_{TH}$ to $(V_{TH} - 100\text{mV})$		20		μs	
$I_{IH(AV)}$	Average High-level Input Current	WDI	WDI= V_{CC} , Time average (dc=88%)	-	120	-	μA
$I_{IL(AV)}$	Average Low-level Input Current		WDI=0.3V, $V_{CC}=5.5\text{V}$ time average (dc=12%)	-	-15	-	μA
I_{IH}	High-level Input Current	WDI	WDI= V_{CC}	-	120	160	μA
I_{IL}	Low-level Input Current	WDI	WDI=0.3V, $V_{CC}=5.5\text{V}$	-	120	160	μA
I_{CC}	Supply Current	WDI and \overline{MR} Unconnected, Outputs unconnected	$V_{CC} = \underline{V_{TH}} + 0.2\text{V}$	-	30	40	μA
	Internal Pull-up Resistor at \overline{MR}			-	60	-	$\text{k}\Omega$
TC	V_{OUT} Temperature Coefficient				50	-	$\text{ppm}/^\circ\text{C}$
C_i	Input Capacitance at \overline{MR} , WDI	$V_I = 0\text{V}$ to 5.5V	-	5	-	pF	
θ_{JA}	Thermal Resistance Junction-to-Ambient	SOT25 (Note 6)		161		$^\circ\text{C}/\text{W}$	
		SOT26 (Note 6)		169			
θ_{JC}	Thermal Resistance Junction-to-Case	SOT25 (Note 6)		27		$^\circ\text{C}/\text{W}$	
		SOT26 (Note 6)		28			

Notes: 4. To ensure best stability of the threshold voltage, a bypass capacitor (ceramic, $0.1\mu\text{F}$) should be placed near the supply terminals.

5. The RESET short-circuit current is the maximum pull-up current when RESET is driven low by a P bidirectional reset pin.

6. Test condition for SOT25 and SOT26: Devices mounted on FR-4 substrate PC board, 2oz copper, with minimum recommended pad layout.


Timing requirements (at $R_L=1\text{m}\Omega$, $C_L=50\text{pF}$, $T_A=25^\circ\text{C}$)

Symbol	Parameter	Test Conditions		Min	Typ.	Max	Unit
t_W	Pulse Width at <u>MR</u>	$V_{CC} \geq V_{TH} + 0.2V$, $V_{IL} = 0.3 \times V_{CC}$, $V_{IH} = 0.7 \times V_{CC}$		100	-	-	ns
	at <u>WDI</u>	$V_{CC} \geq V_{TH} + 0.2V$, $V_{IL} = 0.3 \times V_{CC}$, $V_{IH} = 0.7 \times V_{CC}$		50	-	-	ns


Switching Characteristics (at $R_L=1\text{m}\Omega$, $C_L=50\text{pF}$, $T_A=25^\circ\text{C}$)

Symbol	Parameter	Test Conditions	Min	Typ.	Max	Unit
t_{out}	Watchdog Time Out	APX823/APX824/APX825A $V_{CC} \geq V_{TH} + 0.2V$, See timing diagram	1.12	1.6	2.4	s
t_d	Delay Time	APX823/APX824/APX825A $V_{CC} \geq V_{TH} + 0.2V$, See timing diagram	140	200	280	ms
t_{PHL}	Propagation (Delay) Time, High-to-low-level Output	MR to RESET delay (APX823/APX825A) $V_{CC} > V_{TH} + 0.2V$, $V_{IL} = 0.3 \times V_{CC}$, $V_{IH} = 0.7 \times V_{CC}$	-	-	0.1	μs
		V_{CC} to RESET delay $V_{IL} = V_{TH} - 0.2V$, $V_{IH} = V_{TH} + 0.2V$	-	-	25	μs
t_{PLH}	Propagation (Delay) Time, Low-to-high-level Output	MR to RESET delay (APX824/APX825A) $V_{CC} > V_{TH} + 0.2V$, $V_{IL} = 0.3 \times V_{CC}$, $V_{IH} = 0.7 \times V_{CC}$	-	-	0.1	μs
		V_{CC} to RESET delay (APX824/APX825A) $V_{IL} = V_{TH} - 0.2V$, $V_{IH} = V_{TH} + 0.2V$	-	-	25	μs

Application Circuit






Functional Block Diagram




* APX824/APX825A

** APX823/APX825A

Timing Diagram




Typical Characteristics




Marking Information

(1) SOT25



XX : Identification code
(See Marking Table)
Y : Year: 0-9
M : Month: A~L
G : Green

(2) SOT26




XX : Identification code
(See Marking Table)
Y : Year: 0-9
M : Month: A~L
G : Green

Marking Table


Device	Package Type	Identification Code
APX823-46W5	SOT25	W1
APX823-44W5	SOT25	W2
APX823-40W5	SOT25	W3
APX823-31W5	SOT25	W4
APX823-29W5	SOT25	W5
APX823-26W5	SOT25	W6
APX823-23W5	SOT25	W7
APX824-46W5	SOT25	T2
APX824-44W5	SOT25	T3
APX824-40W5	SOT25	T4
APX824-31W5	SOT25	T5
APX824-29W5	SOT25	T6
APX824-26W5	SOT25	T7
APX824-23W5	SOT25	T8
APX825A-46W6	SOT26	T9
APX825A-44W6	SOT26	TA
APX825A-40W6	SOT26	TB
APX825A-31W6	SOT26	TC
APX825A-29W6	SOT26	TD
APX825A-26W6	SOT26	TE
APX825A-23W6	SOT26	TF

Package Information (All Dimensions in mm)

(1) Package Type: SOT25



(2) Package Type: SOT26



Notes: 7. Package outline dimensions as shown on Diodes Inc. package outline dimensions document AP02002, which can be found on our website at <http://www.diodes.com/datasheets/ap02002.pdf>



APX823/APX824/APX825A

PROCESSOR SUPERVISORY CIRCUITS

IMPORTANT NOTICE

Diodes Incorporated and its subsidiaries reserve the right to make modifications, enhancements, improvements, corrections or other changes without further notice to any product herein. Diodes Incorporated does not assume any liability arising out of the application or use of any product described herein; neither does it convey any license under its patent rights, nor the rights of others. The user of products in such applications shall assume all risks of such use and will agree to hold Diodes Incorporated and all the companies whose products are represented on our website, harmless against all damages.

LIFE SUPPORT

Diodes Incorporated products are not authorized for use as critical components in life support devices or systems without the expressed written approval of the President of Diodes Incorporated.