

S11ME5/S11ME6/S21ME5F S21ME5/S21ME6/S21ME6F

Phototriac Coupler Conformable to European Safety Standard

- * Lead forming type (I type) of / S21ME5F/ S21ME6F are also available. (/ S21ME5FI/ S21ME6FI)
- * DIN-VDE0884 approved type is also available as an option.

■ Features

1. Internal isolation distance : 0.4mm or more
2. Creepage distance : 6.4mm or more
3. Clearance : 6.4mm or more
4. Recognized by UL file No. E64380

Approved by VDE (DIN-VDE0884 : No.76850)

Approved by BSI (BS415 : No.6690, BS7002 : No.7421)

Approved by SEMKO (No.9202227)

Approved by DEMKO (No.107968)

Approved by EI (No.152029-02,03,04,0116)


5. Built-in zero-cross circuit
(S11ME6/S21ME6/S21ME6F)
6. Wide forming type (S21ME5F, S21ME6F)
(Distance between lead pins : 10.16 mm)
7. High isolation voltage between input and output
(Viso : 5 000V_{rms})

■ Applications

1. For triggering medium/high power triac
2. For detecting over voltage of switching power supply

■ Outline Dimensions

(Unit : mm)



■ Absolute Maximum Ratings

(Ta = 25°C)

Parameter		Symbol	Rating	Unit
Input	Forward current	I _F	50	mA
	Reverse voltage	V _R	6	V
Output	RMS ON-state current	I _T	100	mA _{rms}
	*1 Peak one cycle surge current	I _{surge}	1.2	A
	Repetitive peak OFF-state voltage	V _{DRM}	400	V
			*2 S21ME5 / S21ME6	
*3 Isolation voltage		V _{iso}	5 000	V _{rms}
Operating temperature		T _{opr}	- 30 to + 100	°C
Storage temperature		T _{stg}	- 55 to + 125	°C
*4 Soldering temperature		T _{sol}	260	°C

*1 50Hz sine wave *2 Also S21ME5F/ S21ME6F

*3 40 to 60% RH, AC for 1 minute, f = 60Hz

*4 For 10 seconds

■ Electro-optical Characteristics

($T_a = 25^\circ\text{C}$)

Parameter		Symbol	Conditions	MIN.	TYP.	MAX.	Unit
Input	Forward voltage	V_F	$I_F = 20\text{mA}$	-	1.2	1.4	V
	Reverse current	I_R	$V_R = 3\text{V}$	-	-	10^{-5}	A
Output	Repetitive peak OFF-state current	I_{DRM}	$V_{DRM} = \text{Rated}$	-	-	10^{-6}	A
	ON-state voltage	V_T	$I_T = 100\text{mA}$	-	-	2.5	V
	Holding current	I_H	$V_D = 6\text{V}$	0.1	-	3.5	mA
	Critical rate of rise of OFF-state voltage	dV/dt	$V_{DRM} = (1/\sqrt{2}) \cdot \text{Rated}$	100	-	-	$\text{V}/\mu\text{s}$
	*5Zero-cross voltage	V_{OX}	Resistance load, $I_F = 15\text{mA}$	-	-	35	V
	Transfer characteristics	Minimum trigger current	I_{FT}	$R_L = 100\Omega, V_D = 6\text{V}$	-	-	10
Transfer characteristics	Isolation resistance	R_{ISO}	$\text{DC} = 500\text{V}, 40 \text{ to } 60\% \text{ RH}$	5×10^{10}	10^{11}	-	Ω
	Turn-on time	t_{on}	$V_D = 6\text{V}, R_L = 100\Omega, I_F = 20\text{mA}$	-	-	100	μs

*5 S11ME6, S21ME6, S21ME6F

Fig. 1 RMS ON-state Current vs. Ambient Temperature




Fig. 2 Forward Current vs. Ambient Temperature




Fig. 3 Forward Current vs. Forward Voltage




Fig. 4 Minimum Trigger Current vs. Ambient Temperature




Fig. 5 Relative Repetitive Peak OFF-state Voltage vs. Ambient Temperature




Fig. 6 ON-state Voltage vs. Ambient Temperature




Fig. 7 Holding Current vs. Ambient Temperature




Fig. 8-a Repetitive Peak OFF-state Current vs. OFF-state Voltage (S21ME5/S21ME5F)




Fig. 8-b Repetitive Peak OFF-state Current vs. OFF-state Voltage (S21ME6/S21ME6F)




Fig. 9-a Repetitive Peak OFF-state Current vs. Ambient Temperature (S11ME5/S21ME5/S21ME5F)




Fig. 9-b Repetitive Peak OFF-state Current vs. Ambient Temperature (S11ME6/S21ME6/S21ME6F)




Fig.10 Turn-on Time vs. Forward Current




Fig11. Zero-cross Voltage vs. Ambient Temperature (S11ME6/S21ME6/S21ME6F)





Fig.12 ON-state Current vs. ON-state Voltage



- Please refer to the chapter “Precautions for Use.” (Page 78 to 93).

NOTICE

- The circuit application examples in this publication are provided to explain representative applications of SHARP devices and are not intended to guarantee any circuit design or license any intellectual property rights. SHARP takes no responsibility for any problems related to any intellectual property right of a third party resulting from the use of SHARP's devices.
- Contact SHARP in order to obtain the latest device specification sheets before using any SHARP device. SHARP reserves the right to make changes in the specifications, characteristics, data, materials, structure, and other contents described herein at any time without notice in order to improve design or reliability. Manufacturing locations are also subject to change without notice.
- Observe the following points when using any devices in this publication. SHARP takes no responsibility for damage caused by improper use of the devices which does not meet the conditions and absolute maximum ratings to be used specified in the relevant specification sheet nor meet the following conditions:
 - (i) The devices in this publication are designed for use in general electronic equipment designs such as:
 - Personal computers
 - Office automation equipment
 - Telecommunication equipment [terminal]
 - Test and measurement equipment
 - Industrial control
 - Audio visual equipment
 - Consumer electronics
 - (ii) Measures such as fail-safe function and redundant design should be taken to ensure reliability and safety when SHARP devices are used for or in connection with equipment that requires higher reliability such as:
 - Transportation control and safety equipment (i.e., aircraft, trains, automobiles, etc.)
 - Traffic signals
 - Gas leakage sensor breakers
 - Alarm equipment
 - Various safety devices, etc.
 - (iii) SHARP devices shall not be used for or in connection with equipment that requires an extremely high level of reliability and safety such as:
 - Space applications
 - Telecommunication equipment [trunk lines]
 - Nuclear power control equipment
 - Medical and other life support equipment (e.g., scuba).
- Contact a SHARP representative in advance when intending to use SHARP devices for any "specific" applications other than those recommended by SHARP or when it is unclear which category mentioned above controls the intended use.
- If the SHARP devices listed in this publication fall within the scope of strategic products described in the Foreign Exchange and Foreign Trade Control Law of Japan, it is necessary to obtain approval to export such SHARP devices.
- This publication is the proprietary product of SHARP and is copyrighted, with all rights reserved. Under the copyright laws, no part of this publication may be reproduced or transmitted in any form or by any means, electronic or mechanical, for any purpose, in whole or in part, without the express written permission of SHARP. Express written permission is also required before any use of this publication may be made by a third party.
- Contact and consult with a SHARP representative if there are any questions about the contents of this publication.