

Model #: OMNIVS800

Omni VS UPS System



Highlights

800VA line interactive tower UPS Maintains 120V nominal output over an input range of 83 to 132V Workstation optimized features include HID enabled USB port and single line TEL / DSL surge suppression and two surge-only outlets Input: NEMA 5-15P (120V 15A) / Output: 7 NEMA 5-15R (120V) 2 year product warranty / \$200,000 Ultimate Lifetime Insurance (USA, Puerto Rico & Canada only)

Description

Tripp Lite's OMNIVS800 line interactive UPS system offers voltage regulation, surge suppression and long lasting battery support for personal computers, inter-networking equipment and other sensitive electronics. Internal UPS circuits support entry level PC systems for up to 60 minutes during power failures so that connected equipment can be shut down without data loss. Automatic Voltage Regulation (AVR) circuits regulate brownouts as low as 89 volts back to usable levels without using battery power. Offers complete desktop power protection in an attractive black tower configuration. Includes 6 battery supported outlets for computer, monitor and one vital system peripheral, plus 1 additional surge suppression-only outlet for printers and other system accessories not requiring battery support. HID-compliant USB port enables optional unattended system shutdown without data loss in case of extended power failure; USB cable included. HID-compliant USB port also enables direct integration with built-in power management and auto-shutdown features of Windows and MAC OS X. PowerAlert software available via free download from www.tripplite.com. Built-in single line phone/Ethernet suppression jacks protect modem, fax machine, cordless phone or other peripheral with a standard dialup, DSL, or data line connection. Built-in audible alarm and 4 front panel LEDs indicate line power status, battery power status, battery low/replace status and voltage boost operation. 800VA/475 watt power handling ability supports entry-level PCs, network workstations, point-of-sale equipment, small business phone systems, audio/video equipment and home theater systems. Offers 3.5 minutes battery runtime with a full load of 800VA and 11.5 minutes with a half load of 400VA. Supports battery replacement via built-in access panel. 2 year warranty. \$200,000cnnected equipment insurance (USA & Canada Only).

Applications

Entry-level PCs, networked workstations, point-of-sale equipment, small business phone systems, audio/video equipment and home theater systems. Ideal for sensitive electronic applications in areas where brownout conditions are common.

Package Includes

OMNIVS800 Line Interactive UPS USB and telephone cable User manual with warranty information

Features

OMNIVS800 Uninterruptible Power Supply offers voltage regulation, surge suppression and long lasting battery support Supports entry level PCs up to 60 minutes during blackouts to enable shutdown without data loss Regulates brownouts as low as 89 volts back to usable levels without using battery power

Tripp Lite 1111 West 35th Street Chicago, IL 60609 USA Telephone: +(773) 869 1234 E-mail: saleshelp@tripplite.com 6 UPS battery supported/surge protected outlets, plus 1 additional surge suppression-only outlet

Built-in HID-compliant USB port and PowerAlert UPS power management software (available via free download at tripplite.com) and cabling provide monitoring of in-depth site power conditions, full UPS status and fault warnings, and output load level

HID-compliant USB port also enables direct integration with built-in power management and auto-shutdown features of Windows and MAC OS X Single line phone/Ethernet suppression jacks protects standard dialup/DSL, or Ethernet connections

Audible alarm and 4 front panel LEDs offer complete UPS and line power status information

800VA/475 watt power handling ability supports a variety of sensitive electronic equipment

3.5 minutes full load runtime (800VA), 11.5 minutes half load runtime (400VA)

Supports battery replacement via built-in access panel

2 year product warranty.

\$200,000 connected equipment insurance (USA & Canada Only).

Specifications

Voltage compatibility 120V AC Frequency compatibility 60Hz OUTPUT 0utput VA 0utput VA 800 Output watts 475 Output nominal voltage 120v Output voltage regulation BATTERY MODE: PWM sine wave 115V +/-5% Output frequency regulation LINE MODE: Passes line frequency of 60Hz +/-10% BATTERY MODE: Inverter output regulated to 60Hz +/-0.5Hz		
compatibility Image: Compatibility OUTPUT Output VA 800 Output values 475 Output nominal voltage 120v Output voltage BATTERY MODE: PWM sine wave 115V +/-5% Output frequency LINE MODE: Passes line frequency of 60Hz +/-10% BATTERY MODE: Inverter output regulated to 60Hz +/-0.5Hz		
Output VA 800 Output watts 475 Output nominal voltage 120v Output voltage BATTERY MODE: PWM sine wave 115V +/-5% Output frequency LINE MODE: Passes line frequency of 60Hz +/-10% BATTERY MODE: Inverter output regulated to 60Hz +/-0.5Hz		
Output watts 475 Output nominal voltage 120v Output voltage BATTERY MODE: PWM sine wave 115V +/-5% Output frequency LINE MODE: Passes line frequency of 60Hz +/-10% BATTERY MODE: Inverter output regulated to 60Hz +/-0.5Hz		
Output nominal voltage 120v Output voltage regulation BATTERY MODE: PWM sine wave 115V +/-5% Output frequency LINE MODE: Passes line frequency of 60Hz +/-10% BATTERY MODE: Inverter output regulated to 60Hz +/-0.5Hz		
voltage Output voltage BATTERY MODE: PWM sine wave 115V +/-5% regulation LINE MODE: Passes line frequency of 60Hz +/-10% BATTERY MODE: Inverter output regulated to 60Hz +/-0.5Hz		
regulation Output frequency LINE MODE: Passes line frequency of 60Hz +/-10% BATTERY MODE: Inverter output regulated to 60Hz +/-0.5Hz		
regulation		
Outlet quantity / type 7 NEMA 5-15R		
INPUT		
Maximum input amps 12A		
Input connection type NEMA 5-15P, right-angle plug		
Input cord length 6 ft., 14 gauge		
Recommended 15A 120V electrical service		
BATTERY		
Full load runtime 3.5 minutes (800VA)		
Half load runtime 11.5 minutes (400VA)		
DC system voltage 12VDC		
Typical battery 4-6 years typical lifespan -6 years typical		
Battery recharge rate 2-4 hours to 90%		
Replacement Battery RBC51 Cartridge Carterian		
VOLTAGE REGULATION		
Voltage regulation description Line interactive voltage regulation corrects brownouts as low as 83V back to usable values		
Direct pass through Voltages of 106V and greater are passed through to connected equipment unchanged		
Brownout correction Input voltages between 83 and 105 are boosted by 14%		
LEDS ALARMS & SWITCHES		
Front panel LEDs 4 front panel LEDs indicate line power status, battery power status, battery low/replace status and voltage regulation		

Alarms	Audible alarm with 15 second delay sounds to indicate loss of utility power. Alarm can be silenced by pressing front panel alarm cancel button. Once silenced, alarm will re-sound when approximately 2 minutes runtime remain.
Switches	Includes 2 front panel switches - one main on/off power switch and one dual function "alarm cancel" / "self test" button
SURGE / NOISE SUPPR	ESSION
AC surge suppression	480 joules
AC suppression response time	Instantaneous
Dataline suppression	Tel/DSL/Ethernet
EMI / RFI AC noise suppression	Yes
PHYSICAL	
Shipping weight (Ibs)	23.2
Shipping weight (kg)	10.5
Shipping Dimensions (HWD/in)	14 x 8.5 x 10.5
Shipping Dimensions (HWD/cm)	35.6 x 21.6 x 26.7
Unit weight (Ibs)	21.2
Unit weight (kg)	9.6
Unit Dimensions (HWD/in)	10.75 x 5.25 x 7.25
Unit Dimensions (HWD/cm)	27.3 x 13.4 x 18.4
Material of construction	PVC
Form factors supported	Tower
Cooling method	Convection
Battery Access	Battery access door allows user replacement of UPS batteries.
ENVIRONMENTAL	
Operating Temperature	+32 to +104 degrees Fahrenheit / 0 to +40 degrees Celsius
Storage Temperature	+5 to +122 degrees Fahrenheit / -15 to +50 degrees Celsius
Relative Humidity	0 to 95%, non-condensing
COMMUNICATIONS	
Network monitoring port	USB (HID)
Software and cabling included	USB cabling included, PowerAlert software available for free download at www.tripplite.com
WatchDog compatibility	Yes, compatible with Tripp Lite's Watchdog system service to restore operation to locked equipment through soft reboot of application / OS or hard power off/on reboot of connected equipment — ideal for unattended kiosk applications
LINE / BATTERY TRAN	SFER
Transfer time from line power to battery mode	2-4 milliseconds
Low voltage transfer to battery power	Switches to battery power as line voltage decreases to 83 volts or less. Resets to line power mode as line voltage increases to 87V or higher
High voltage transfer to battery power	Switches to battery power as line voltage increases to 147 volts or higher. Resets to line power mode as line voltage decreases to 143V or less.
CERTIFICATIONS	

Certifications	Tested to UL1778 (USA), CSA C22.2 No. 107.3 (Canada), Class B (emissions), NOM (Mexico), FCC Part 68 / Industry Canada (telecommunications), RoHS Compliant
WARRANTY	
Product warranty	2 year product warranty
Connected equipment insurance (USA and Canada Only	\$200,000 connected equipment insurance (USA and Canada only)
Optional coverage	3-5 year warranties, plus next day and on-site warranty coverage available. Contact Tripp Lite for additional information.
SPECIAL FEATURES	
Cold Start	Yes, inverter can be "cold started" to enable temporary AC output during a power failure
Appearance	Attractive black color appearance

More information, including related products, owner's manuals, and additional technical specifications, can be found online at www.tripplite.com/products/model.cfm?txtModelID=2729.

©2008 Tripp Lite. All Rights Reserved.