



STM32-SK/IAR STR91X-SK/IAR, STR7-SK/IAR

IAR™ starter kits for ST ARM core-based microcontrollers

Data Brief

Features


- The IAR Embedded WorkBench™ for ARM® (EWARM) software package with:
 - KickStart™ C/C++ compiler for output of code up to 32 Kbytes
 - VisualState™ code generator, 20-state version
 - C-SPY high-level language debugger
 - Editor, linker and librarian tools
- J-Link in-circuit debugger/programmer with USB interface to host PC and 20-pin JTAG application interface (embedded on some kits)
- Full-featured KickStart™ development board with target microcontroller. On-board features are listed in [Table 1](#).

Description

The **IAR KickStart kits** are complete, cost-effective solutions for starting application development and evaluating STMicroelectronics' ARM core-based microcontrollers.

The KickStart kit's come with all the hardware and software you need to start developing applications including the KickStart development board with target microcontroller, the IAR J-Link in-circuit debugger/programmer (USB/JTAG) and IAR Embedded Workbench™ for ARM (EWARM) integrated development environment with the KickStart edition of the IAR C/C++ compiler (output code up to 32 Kbytes), built-in Flash loader and sample projects for all device peripherals.

IAR KickStart kits provide evaluation and development support for a full range of ST ARM core-based microcontrollers.



Starter kit architecture

The **IAR development software** is a suite of software tools for all phases of application development that includes:

- **IAR Embedded Workbench for ARM** integrated development environment with the KickStart 32KB C/C++ compiler to build the application and the C-SPY™ debugger for debugging the application while it runs on your microcontroller.
- **VisualSTATE 20-state version** of IAR's graphical design environment with C/C++ code generator for developing application code based on machine states.
- **J-Link** in-circuit debugger/programmer (USB/JTAG) which integrates fully with EWARM, allowing you to download the application to your target and debug it while it runs on your ST ARM core-based microcontroller. J-Link is embedded on the KickStart development board in the STM32F10xE starter kit.
- **KickStart development board** that provides a full range of features to help developers evaluate and start developing applications for the included microcontroller. The board is powered from the J-Link's USB connection with the host PC.

Table 1. KickStart development board key features

Feature	Starter kit							
	STM32F10xE	STM32F10xB	STR91xF	STR75xF	STR731F	STR730F	STR712F	STR711F
Included microcontroller	STM32F103E	STM32F103B	STR912FAW4	STR750FV2	STR731FV2	STR730FZ2	STR712FR2	STR711FR2
J-Link	Embedded	Standalone	Standalone	Standalone	Standalone	Standalone	Standalone	Standalone
20-pin JTAG connector	Yes	Yes	Yes	Yes	Yes	Yes	Yes	Yes
Trace tool connector	20-pin	N/A	38-pin	N/A	N/A	N/A	N/A	N/A
Power supply from USB connection	Yes	Yes	Yes	Yes	Yes	Yes	Yes	Yes
Backup power supply	No	No	3V button battery	No	No	No	No	No
USART connector(s)	2	2	3	3	4	4	2	2
SPI	Yes	Yes	Yes	Yes	Yes	Yes	Yes	Yes
I ² C	Yes	Yes	Yes	Yes	Yes	Yes	Yes	Yes
CAN connector	No	Yes	Yes	Yes	No	Yes	Yes	No
USB connector	Yes	Yes	Yes	Yes	Yes	No	No	Yes

Table 1. KickStart development board key features (continued)

Feature	Starter kit							
	STM32F10xE	STM32F10xB	STR91xF	STR75xF	STR731F	STR730F	STR712F	STR711F
Ethernet connector	N/A	N/A	Yes	N/A	N/A	N/A	N/A	N/A
User LEDs	4	16	16	16	16	16	2	2
LCD display	Graphical	Yes (2x16)	Yes (2x16)	Yes (2x16)	Yes (2x16)	Yes (2x16)	No	No
SD/MMC connector	Yes	Yes	Yes	Yes	No	No	No	No
Potentiometer connected to ADC	Yes	Yes	Yes	Yes	Yes	Yes	Yes	Yes
User and wake-up push button(s)	3	4	3	5	5	5	3	3
Reset button	Yes	Yes	Yes	Yes	Yes	Yes	Yes	Yes
Wrap area	Yes	Yes	Yes	Yes	Yes	Yes	Yes	Yes
Additional features								
Stepper motor	Yes	No	No	No	No	No	No	No
MEMS accelerometer	Yes	No	No	No	No	No	No	No

Ordering information

IAR KickStart kits can be ordered from IAR or from your nearest ST distributor or sales office. Kits are currently available for:

- STM32F10xE microcontrollers (ST order code: **STM3210E-SK/IAR**)
- STM32F10xB microcontrollers (ST order code: **STM3210B-SK/IAR**)
- STR91xF microcontrollers (ST order code: **STR91X-SK/IAR**)
- STR75xF microcontrollers (ST order code: **STR750-SK/IAR**)
- STR731F microcontrollers (ST order code: **STR731-SK/IAR**)
- STR730F microcontrollers (ST order code: **STR730-SK/IAR**)
- STR712F microcontrollers (ST order code: **STR712-SK/IAR**)
- STR711F microcontrollers (ST order code: **STR711-SK/IAR**)

For more information and complete documentation, please refer to the IAR web site or the STMicroelectronics microcontroller support site on www.st.com.

Revision history

Table 2. Document revision history

Date	Revision	Changes
1-Apr-2005	1	Initial release.
27-Sep-2005	2	Added STR730-SK/IAR and table of on-board features.
7-Jun-2006	3	Added STR91X-SK/IAR and STR731-SK/IAR and key features.
4-Oct-2006	4	Added STR750-SK/IAR and key features.
4-Oct-2007	5	Modified document title. Added STM3210B-SK/IAR and key features.
17-Oct-2008	6	Added STM3210E-SK/IAR and key features.

Please Read Carefully:

Information in this document is provided solely in connection with ST products. STMicroelectronics NV and its subsidiaries ("ST") reserve the right to make changes, corrections, modifications or improvements, to this document, and the products and services described herein at any time, without notice.

All ST products are sold pursuant to ST's terms and conditions of sale.

Purchasers are solely responsible for the choice, selection and use of the ST products and services described herein, and ST assumes no liability whatsoever relating to the choice, selection or use of the ST products and services described herein.

No license, express or implied, by estoppel or otherwise, to any intellectual property rights is granted under this document. If any part of this document refers to any third party products or services it shall not be deemed a license grant by ST for the use of such third party products or services, or any intellectual property contained therein or considered as a warranty covering the use in any manner whatsoever of such third party products or services or any intellectual property contained therein.

UNLESS OTHERWISE SET FORTH IN ST'S TERMS AND CONDITIONS OF SALE ST DISCLAIMS ANY EXPRESS OR IMPLIED WARRANTY WITH RESPECT TO THE USE AND/OR SALE OF ST PRODUCTS INCLUDING WITHOUT LIMITATION IMPLIED WARRANTIES OF MERCHANTABILITY, FITNESS FOR A PARTICULAR PURPOSE (AND THEIR EQUIVALENTS UNDER THE LAWS OF ANY JURISDICTION), OR INFRINGEMENT OF ANY PATENT, COPYRIGHT OR OTHER INTELLECTUAL PROPERTY RIGHT.

UNLESS EXPRESSLY APPROVED IN WRITING BY AN AUTHORIZED ST REPRESENTATIVE, ST PRODUCTS ARE NOT RECOMMENDED, AUTHORIZED OR WARRANTED FOR USE IN MILITARY, AIR CRAFT, SPACE, LIFE SAVING, OR LIFE SUSTAINING APPLICATIONS, NOR IN PRODUCTS OR SYSTEMS WHERE FAILURE OR MALFUNCTION MAY RESULT IN PERSONAL INJURY, DEATH, OR SEVERE PROPERTY OR ENVIRONMENTAL DAMAGE. ST PRODUCTS WHICH ARE NOT SPECIFIED AS "AUTOMOTIVE GRADE" MAY ONLY BE USED IN AUTOMOTIVE APPLICATIONS AT USER'S OWN RISK.

Resale of ST products with provisions different from the statements and/or technical features set forth in this document shall immediately void any warranty granted by ST for the ST product or service described herein and shall not create or extend in any manner whatsoever, any liability of ST.

ST and the ST logo are trademarks or registered trademarks of ST in various countries.

Information in this document supersedes and replaces all information previously supplied.

The ST logo is a registered trademark of STMicroelectronics. All other names are the property of their respective owners.

© 2008 STMicroelectronics - All rights reserved

STMicroelectronics group of companies

Australia - Belgium - Brazil - Canada - China - Czech Republic - Finland - France - Germany - Hong Kong - India - Israel - Italy - Japan - Malaysia - Malta - Morocco - Singapore - Spain - Sweden - Switzerland - United Kingdom - United States of America

www.st.com