

# Function Generators



4011A



4010A

## Model 4011A 5 MHz Function Generator with Digital Display

- 0.5 Hz to 5 MHz
- Sine, Square, Triangle, Pulse, & Ramp output
- Coarse and Fine tuning
- 4 digit LED display
- Variable duty cycle
- Variable DC offset

## Model 4010A 2 MHz Function Generator

- 0.2 Hz to 2 MHz
- Sine, Square, Triangle, Pulse, & Ramp output
- Variable duty cycle
- Variable DC offset

## Specifications

models  
4011A 4010A

	4011A	4010A
<b>Frequency Characteristics</b>		
Waveforms	Sine, Square, Triangle, $\pm$ Pulse, $\pm$ Ramp	
Range	0.5 Hz to 5 MHz	0.2 Hz to 2 MHz
	in 7 ranges	
Resolution	4 digits	NA
Dial Accuracy	NA	$\pm$ 5% typical
Tuning Range	Coarse, 10:1	10:1
	Fine $\pm$ 5% of coarse setting	
Variable Duty Cycle	15:85:15 Cont variable	15:85:15 cont variable
Operating Modes	Normal, VCG	Normal, VCG
<b>Output Characteristics</b>		
Impedance	50 $\Omega$ $\pm$ 10%	
Level	20 V p-p Open circuit, 10V p-p into 50 $\Omega$	
Amplitude	Variable, 20 dB range typical	
Attenuation	-20 dB $\pm$ 1dB	
DC Offset	Preset $\pm$ 0.1 V typ Variable: $\pm$ 10V open-circuit $\pm$ 5 into 50 $\Omega$	
SINE Wave	Distortion: $\leq$ 3% @ 1 kHz Flatness: $\pm$ 5% (.45 dB)	Distortion: $\leq$ 4% @ 1 kHz Flatness: $\pm$ 5% (.45 dB)
Square Wave	Symmetry: 0.5 Hz to 100 KHz $\leq$ 2% Risettime: $\leq$ 120 nS	
Triangle Wave	Linearity: $\geq$ 98% to 100 KHz, $\geq$ 95% to 2 MHz	
<b>TTL Output</b>		
Level	0.8V to 2.4V	
Rise time	$\leq$ 20 nS (4011A), $\leq$ 50 nS (4010A)	
Duty Cycle	50% typical	
<b>CMOS Output</b>		
Max. Frequency	2 MHz	2 MHz
Level	4V to 14V $\pm$ 0.5 p-p cont. variable	
Rise Time	$\leq$ 120 nS	
<b>Input</b>		
Input Voltage	0-10V $\pm$ 1V causes a 100:1 frequency change	
Impedance	10K $\Omega$ $\pm$ 5%	
<b>Frequency Counter</b>		
Accuracy	Time Base Accy $\pm$ 1 count	NA
Time Base Accuracy	$\pm$ 10 PPM (23°C $\pm$ 5°C)	NA
Display	4 digit LED	NA
Power Source	120/230 VAC $\pm$ 10%, 50/60 Hz, internal jumper selectable	
Dimensions (H x W x D)	4.5 x 11.75 x 10.375" (114 x 298 x 264 mm)	
Weight	4 lbs (1.8 kg)	

## Accessories

Two Year Warranty

SUPPLIED: Output cable with BNC to alligator clips, Instruction Manual  
Carrying Case (not included): LC-40