

Audio Transformer

PC Mount

TY-145P

Description:

These transformers operate in the 200 Hz to 15,000 Hz range, making them suitable for a broad application spectrum in the audio industry. These devices are used in line matching, telephone coupling, pulse trigger, driver, interstage, output, isolation and input applications.

Operating Temperature Range: 0° C to 105° C

Electrical Specifications at 25° C:

1. Primary Impedance: 600Ω CT

+ 15% with 600Ω load

 $\begin{array}{lll} \text{2.} & \text{Secondary Impedance:} & 600\Omega \text{ CT} \\ \text{3.} & \text{Output:} & 100\text{mW} \\ \text{4.} & \text{Primary DC Unbalance:} & 15 \text{ Ma} \\ \end{array}$

5. Frequency Response: <u>+</u> 2db from 200 to 15,000 Hz
6. Impedance Matching: <u>+</u> 2db from 200 to 15,000 Hz

7. Longitudinal Balance > 45db8. Insertion Loss @ 1K Hz: < 1.5db9. Return Loss: > 26db

10. Total Harmonic Distortion < 0.5% between 275Hz and 3.5KHz

11. DCR:

Primary (1-3) 44Ω Nominal Secondary (4-6) 58Ω Nominal

12. Turns Ratio: 1 : 1

13. Dielectric Strength 1500V Pri to Sec to Core

Construction:


Bobbin has plug-in terminals which are spaced to provide fixed mounting centers. Pins are a rugged .042" square, minimizing the incidence of bent pins from handling.

Outline Dimensions:

A. Dimensions: As figures show B. PIN DIM.: .0375" x .020"

C. Weight.: 0.51 oz.

Schematic:




RoHS Compliance: As of manufacturing date February 2005, all standardproducts meet the requirements of 2002/95/EC, known as the RoHS initiative.


*Upon printing, this document is considered "uncontrolled".Please contact Triad Magnetics' website for the most current version.


web:www.TriadMagnetics.com 22520 Phone 951-277-0757 Corona Fax 951-277-2757 92883

22520B Temescal Canyon Road Corona ,California 92883









Publish Date: June 20, 2006