

**PCI2050**

<b>Last Update:</b>	<b>9/23/05</b>
---------------------	----------------

Errata

Index

---

1      Trst – CLK timing is out of specification

---

---

---

## Errata #1

### Brief Description of Issue

Trst – CLK timing is out of specification.

### Detailed Description of Issue

When PCI2050B is in 66 MHz primary, 33 MHz secondary mode, the dividing DFF is in reset when primary reset is asserted, so SCLK outputs will stay low when primary reset is asserted and the 66/33 mode is selected. When primary reset is de-asserted, the design will always have 22 secondary PCI clock cycles from the removal of primary bus reset (and the secondary bus clock starting) to the removal of secondary bus reset. So to calculate that time, it is  $22 * (1/33) = 667$  ns. However, according to the PCI specification, S\_CLK should become active 100 us before S\_RST is de-asserted. So PCI2050B is out of PCI specification. The problem does not exist when PCI2050B is in 66 MHz primary, 66 MHz secondary mode or 33 MHz primary, or 33 MHz secondary mode.

### Impact to Customer & Probability of Bug Occurring in Actual Applications

PCI2050B has been used extensively in the field, and to date, no incompatibilities have been reported.

### SW or HW Workarounds Defined

After the de-assertion of the primary reset, write a '1' to bit 6 of the Bridge Control Register to initiate a secondary bus reset. Then after 100us, write a '0' to bit 6 of the Bridge Control Register to de-assert the secondary bus reset.

Add a circuit to the S\_RST# to delay the de-assertion of secondary bus reset by 100us. .

### Affected Devices

PCI2050A, PCI2050B

## IMPORTANT NOTICE

Texas Instruments Incorporated and its subsidiaries (TI) reserve the right to make corrections, modifications, enhancements, improvements, and other changes to its products and services at any time and to discontinue any product or service without notice. Customers should obtain the latest relevant information before placing orders and should verify that such information is current and complete. All products are sold subject to TI's terms and conditions of sale supplied at the time of order acknowledgment.

TI warrants performance of its hardware products to the specifications applicable at the time of sale in accordance with TI's standard warranty. Testing and other quality control techniques are used to the extent TI deems necessary to support this warranty. Except where mandated by government requirements, testing of all parameters of each product is not necessarily performed.

TI assumes no liability for applications assistance or customer product design. Customers are responsible for their products and applications using TI components. To minimize the risks associated with customer products and applications, customers should provide adequate design and operating safeguards.

TI does not warrant or represent that any license, either express or implied, is granted under any TI patent right, copyright, mask work right, or other TI intellectual property right relating to any combination, machine, or process in which TI products or services are used. Information published by TI regarding third-party products or services does not constitute a license from TI to use such products or services or a warranty or endorsement thereof. Use of such information may require a license from a third party under the patents or other intellectual property of the third party, or a license from TI under the patents or other intellectual property of TI.

Reproduction of information in TI data books or data sheets is permissible only if reproduction is without alteration and is accompanied by all associated warranties, conditions, limitations, and notices. Reproduction of this information with alteration is an unfair and deceptive business practice. TI is not responsible or liable for such altered documentation.

Resale of TI products or services with statements different from or beyond the parameters stated by TI for that product or service voids all express and any implied warranties for the associated TI product or service and is an unfair and deceptive business practice. TI is not responsible or liable for any such statements.

Following are URLs where you can obtain information on other Texas Instruments products and application solutions:

<b>Products</b>		<b>Applications</b>	
Amplifiers	<a href="http://amplifier.ti.com">amplifier.ti.com</a>	Audio	<a href="http://www.ti.com/audio">www.ti.com/audio</a>
Data Converters	<a href="http://dataconverter.ti.com">dataconverter.ti.com</a>	Automotive	<a href="http://www.ti.com/automotive">www.ti.com/automotive</a>
DSP	<a href="http://dsp.ti.com">dsp.ti.com</a>	Broadband	<a href="http://www.ti.com/broadband">www.ti.com/broadband</a>
Interface	<a href="http://interface.ti.com">interface.ti.com</a>	Digital Control	<a href="http://www.ti.com/digitalcontrol">www.ti.com/digitalcontrol</a>
Logic	<a href="http://logic.ti.com">logic.ti.com</a>	Military	<a href="http://www.ti.com/military">www.ti.com/military</a>
Power Mgmt	<a href="http://power.ti.com">power.ti.com</a>	Optical Networking	<a href="http://www.ti.com/opticalnetwork">www.ti.com/opticalnetwork</a>
Microcontrollers	<a href="http://microcontroller.ti.com">microcontroller.ti.com</a>	Security	<a href="http://www.ti.com/security">www.ti.com/security</a>
		Telephony	<a href="http://www.ti.com/telephony">www.ti.com/telephony</a>
		Video & Imaging	<a href="http://www.ti.com/video">www.ti.com/video</a>
		Wireless	<a href="http://www.ti.com/wireless">www.ti.com/wireless</a>

Mailing Address: Texas Instruments  
Post Office Box 655303 Dallas, Texas 75265