



<b>tyco</b> Electronics		TYCO ELECTRONICS CORPORATION OOSTKAMP - BELGIUM	SCALE DIMENSIONS IN MM	WEIGHT
DATE	07.06.94	LOC	PART NAME Receptacle Assembly Eurocard	
NAME	Cluvelier	DEP.	Press fit, Types B, C and short versions	
REV.	D2 SR10-0177-03 18 JUN 03 KV	APP.	PART NO.	SHT. 1*
REV.	D1 SR10-0244-02 22 MAY 04 BC	APP.	V42254-P2***-C***-7626	of 2
REV. CHANGE ORDER		DATE	Customer Drawing Nr. C. 1593637-7	

Old Part Number	Tyco Part Number	Style & Number of Positions	Termination posts	Loaded Rows	Performance Level	Board Locks
V42254-P2163-C483	1393637-6	C48	3.7mm Press-in terminals	row a+c , every pitch	1	No
V42254-P2163-C960	1393637-7	C96	3.7mm Press-in terminals	every row , every pitch	1	No
V42254-P2163-C963	1393637-9	C96	3.7mm Press-in terminals	row a+c , every pitch	1	No
V42254-P2167-C960	1-1393637-0	C96	17mm Press-in terminals with wire-wrap and insertion area level 2	every row , every pitch	1	No
V42254-P2170-C960	1-1393637-2	C96	6.0mm Press-in terminals	every row , every pitch	1	No
V42254-P2260-B640	1-1393637-9	B64	13mm Press-in terminals with wire-wrap	every row , every pitch	2	No
V42254-P2260-B640N	2-1393637-0	B64	13mm Press-in terminals with wire-wrap	every row , every pitch	2	No
V42254-P2260-C480	2-1393637-2	C48	13mm Press-in terminals with wire-wrap	every row , every pitch	2	No
V42254-P2260-C960	2-1393637-3	C96	13mm Press-in terminals with wire-wrap	every row , every pitch	2	No
V42254-P2260-C962	2-1393637-5	C96	13mm Press-in terminals with wire-wrap	row a+b , every pitch	2	No
V42254-P2260-C963	2-1393637-6	C96	13mm Press-in terminals with wire-wrap	row a+c , every pitch	2	No
V42254-P2261-B640	2-1393637-8	B64	17mm Press-in terminals with wire-wrap	every row , every pitch	2	No
V42254-P2261-C960	2-1393637-9	C96	17mm Press-in terminals with wire-wrap	every row , every pitch	2	No
V42254-P2261-C963	3-1393637-0	C96	17mm Press-in terminals with wire-wrap	row a+c , every pitch	2	No
V42254-P2263-B320	3-1393637-3	B32	3.7mm Press-in terminals	every row , every pitch	2	No
V42254-P2263-B325	3-1393637-4	B32	3.7mm Press-in terminals	every row , every even pitch	2	No
V42254-P2263-B325N	3-1393637-5	B32	3.7mm Press-in terminals	every row , every even pitch	2	No
V42254-P2263-B640	3-1393637-6	B64	3.7mm Press-in terminals	every row , every pitch	2	No
V42254-P2263-C300	4-1393637-0	C30	3.7mm Press-in terminals	every row , every pitch	2	No
V42254-P2263-C303	4-1393637-2	C30	3.7mm Press-in terminals	row a+c , every pitch	2	No
V42254-P2263-C480	4-1393637-4	C48	3.7mm Press-in terminals	every row , every pitch	2	No
V42254-P2263-C480N	4-1393637-5	C48	3.7mm Press-in terminals	every row , every pitch	2	No
V42254-P2263-C483	2-1392009-7	C48	3.7mm Press-in terminals	row a+c , every pitch	2	No
V42254-P2263-C960	4-1393637-6	C96	3.7mm Press-in terminals	every row , every pitch	2	No
V42254-P2263-C963	4-1393637-9	C96	3.7mm Press-in terminals	row a+c , every pitch	2	No
V42254-P2263-C965	5-1393637-2	C96	3.7mm Press-in terminals	every row , every even pitch	2	No
V42254-P2263-C968	5-1393637-3	C96	3.7mm Press-in terminals	row a+c , every even pitch	2	No
V42254-P2266-B320	6-1393637-2	B32	13mm Press-in terminals with wire-wrap and insertion area level 2	every row , every pitch	2	No
V42254-P2266-B640	6-1393637-3	B64	13mm Press-in terminals with wire-wrap and insertion area level 2	every row , every pitch	2	No
V42254-P2266-C480	6-1393637-5	C48	13mm Press-in terminals with wire-wrap and insertion area level 2	every row , every pitch	2	No
V42254-P2266-C960	6-1393637-6	C96	13mm Press-in terminals with wire-wrap and insertion area level 2	every row , every pitch	2	No
V42254-P2266-C963	6-1393637-9	C96	13mm Press-in terminals with wire-wrap and insertion area level 2	row a+c , every pitch	2	No
V42254-P2266-C965	7-1393637-0	C96	13mm Press-in terminals with wire-wrap and insertion area level 2	every row , every even pitch	2	No
V42254-P2266-C968	7-1393637-1	C96	13mm Press-in terminals with wire-wrap and insertion area level 2	row a+c , every even pitch	2	No
V42254-P2267-C960	7-1393637-3	C96	17mm Press-in terminals with wire-wrap and insertion area level 2	every row , every pitch	2	No
V42254-P2267-C963	7-1393637-4	C96	17mm Press-in terminals with wire-wrap and insertion area level 2	row a+c , every pitch	2	No
V42254-P2270-C483	2-1392009-0	C48	6.0mm Press-in terminals	row a+c , every pitch	2	No
V42254-P2270-C960	8-1393637-0	C96	6.0mm Press-in terminals	every row , every pitch	2	No
V42254-P2270-C960N	8-1393637-2	C96	6.0mm Press-in terminals	every row , every pitch	2	No
V42254-P2270-C963	8-1393637-4	C96	6.0mm Press-in terminals	row a+c , every pitch	2	No
V42254-P2270-C963N	8-1393637-6	C96	6.0mm Press-in terminals	row a+c , every pitch	2	No
V42254-P2270-C968	8-1393637-7	C96	6.0mm Press-in terminals	row a+c , every even pitch	2	No
V42254-P2470-C960	1-1393638-2	C96	6.0mm Press-in terminals	every row , every pitch	1	No
V42254-P2470-C963	1-1393638-3	C96	6.0mm Press-in terminals	row a+c , every pitch	1	No

1) Connectors without marking, in Tyco Electronics packaging.

Active part numbers.

Contact Tyco Electronics for other configuration availability

THIS INFORMATION IS CONFIDENTIAL AND PROPRIETARY TO TYCO ELECTRONICS CORPORATION AND ITS WORLDWIDE SUBSIDIARIES AND AFFILIATES. IT MAY NOT BE DISCLOSED TO ANYONE, OTHER THAN TYCO ELECTRONICS PERSONNEL, WITHOUT WRITTEN AUTHORIZATION FROM TYCO ELECTRONICS CORPORATION, HARRISBURG PENNSYLVANIA USA.

<b>tyco</b>		TYCO ELECTRONICS CORPORATION		SCALE		WEIGHT	
<b>Electronics</b>		OOSTKAMP - BELGIUM		MATERIAL			
		DATE 07.06.94		PART NAME			
		NAME Cuvellier		Receptacle Assembly Eurocard			
		APP. PD COM		Press fit, Types B, C and short versions			
		TOLERANCE UNLESS SPECIFIED OTHERWISE		PART NO.		SHT. 2-	
D2 see page 1		V42254-P2***-C***-*-7626					
REV. CHANGE ORDER		DATE		APP. Customer Drawing Nr. C 1393637-7		OF 2	