





Single-Stud Terminals

		WF 6 new	WF 8 new	WF 10 new	WF 12 new
					
Available Options	Version	Part No.	Part No.	Part No.	Part No.
	Beige Wemid	1780850000	1780860000	1780870000	1780880000
Dimensions					
Width / Length / Height mm (in.) with TS 35 x 7.5		19.6/67/56 (0.77/2.64/2.20)	24.6/67/65 (0.97/2.64/2.56)	35.6/67/74 (1.40/2.64/2.91)	35.6/67/72 (1.40/2.64/2.83)
Pitch with partition mm (in.)		18 (0.71)	23 (0.91)	34 (1.34)	34 (1.34)
Stud size		M6	M8	M10	M12
Technical Data					
Rated voltage / rated current / wire size	UL	1000 V / 115 A / #14...2 AWG	1000 V / 150 A / #14...1/0 AWG	1000 V / 255 A / 10...250 MCM	1000 V / 255 A / 10...250 MCM
	CSA	1000 V / 150 A / #14...2 AWG	1000 V / 200 A / #14...1/0 AWG	1000 V / 320 A / 10...250 MCM	1000 V / 320 A / 10...250 MCM
	VDE	800 V / - / -	800 V / - / -	800 V / - / -	800 V / - / -
Torque	Nm (lb. in.)	3...6 (26.5...53.1)	6...12 (53.1...106.2)	10...20 (88.5...177)	14...31 (123...274)
Partition (thickness mm)		Type	Part No.	Type	Part No.
Width / Length / Height mm (in.)		2/101.8/58.5 (0.08/4.01/2.30)	2/109.8/67 (0.08/4.32/2.64)	2/156/76.5 (0.08/6.14/3.01)	2/156/76.5 (0.08/6.14/3.01)
	Beige Wemid	WTW WF 6	1781220000	WTW WF 8	1780900000
	Epoxy resin	WTW WF 6 2300	1781230000	WTW WF 8 2300	1780910000
	Beige Wemid 50 mm long (for insulated cable lugs)	WTW WF 50	1781240000	WTW WF 50	1781240000
Jumpers					
	2 pole	WQL 2 WF 6	1780970000	WQL 2 WF 8	1780990000
	3 pole	WQL 3 WF 6	1780980000	WQL 3 WF 8	1781000000
				WQL 2 WF 10	1781010000
				WQL 3 WF 10	1781020000
				WQL 2 WF 12	1781030000
				WQL 3 WF 12	1781040000
Cover (1m)					
	Transparent PVC	ADP WF 6/WF 8	1780930000	ADP WF 10/WF 12	1780940000
Holder for cover					
	Beige Wemid	HA WF	1781050000	HA WF	1781050000
Marking Tags					
	Print				
	Consecutive horizontal	DEK 5/5	0473460001	DEK 5/5	0473460001
	Consecutive vertical	DEK 5/5	0473560001	DEK 5/5	0473560001
Note: Part numbers shown are for a single card of pre-printed tags numbered 1-50. For additional information, see Accessories section.					

See Accessories section for mounting rails, end brackets, additional marking material and accessories.