



SMART2200RML2U Estimated Runtime

Load in Watts

UPS	Battery Pack	500W	600W	700W	800W	900W	1,000W	1,100W	1,200W	1,300W	1,400W	1,500W	1,600W
SMART2200RML2U	Internal Batteries	27	22	18	16	13	11	9.5	8.3	7.5	7.0	6.5	6.0
SMART2200RML2U	1 BP48V24-2U	109	88	73	62	53	46	41	36	32	29	27	25
SMART2200RML2U	1 BP48V60RT3U	219	179	150	129	111	97	85	76	69	63	57	53
SMART2200RML2U	2 BP48V60RT3U	439	362	306	264	229	202	179	161	146	133	122	113
SMART2200RML2U	3 BP48V60RT3U	658	546	465	403	351	311	278	250	228	208	192	177
SMART2200RML2U	4 BP48V60RT3U	876	730	624	543	475	421	377	341	311	285	263	244
SMART2200RML2U	5 BP48V60RT3U	1,091	912	781	682	598	531	477	432	394	362	335	311
SMART2200RML2U	6 BP48V60RT3U	1,302	1,091	937	820	720	641	576	523	478	440	407	378
SMART2200RML2U	7 BP48V60RT3U	1,510	1,269	1,092	957	841	750	675	614	561	517	479	445
SMART2200RML2U	8 BP48V60RT3U	1,715	1,444	1,245	1,093	962	858	774	704	645	594	551	513
SMART2200RML2U	9 BP48V60RT3U	1,917	1,617	1,396	1,227	1,082	966	872	794	728	672	623	580
SMART2200RML2U	10 BP48V60RT3U	2,116	1,788	1,546	1,360	1,201	1,074	970	884	811	748	695	648

All runtime values are in minutes.