Wiring:

DC POWER SUPPLY



protection.Low Cost

Features:

- · Regulated DC output
- · Snap-track mounted
- · Screw terminals with pressure plates

mounting track for easy field application.

OUTPUT REGULATED 24 VAC DC VOLTAGE ADJUSTMENT OUTPUT

Specifications:

Voltage:	
Input :	24 VAC, 50/60 Hz
Output:	24VDC (full wave rectified and regulated) adjustable 1.5V - 29 VDC
Output Current:	0.5 amps
Over-current Protection:	1 amp fuse
Environment:	
Operating Temperature:	0 to 55 °C
Max. Humidity:	95% RH, noncondensing
Weight:	0.25 lb.
Mounting:	snap-track included

The Model PW 1.0 is a regulated .5 amp power supply that accepts 24 VAC at the input and provides 24 VDC at the output. The PW 1.0 can be ordered with any output voltage from the 1.5V to 29 VDC. Field voltage adjustments may also be made using only a screwdriver. The power supply is provided with a

These low cost power supplies feature good regulation and have full overcurrent

Ordering Information:

PW1.0DC Power Supply CPTR40VA......120/24Vac 40VA Transformer



C-TON Industries • PO Box 10129 • Bedford, NH, 03110 • USA 03110-0129